


# Automation1 XL2e High-Performance Linear Digital Drive

## HARDWARE MANUAL

Revision 1.02



## GLOBAL TECHNICAL SUPPORT

Go to the [Global Technical Support Portal](#) for information and support about your Aerotech, Inc. products. The website supplies software, product manuals, Help files, training schedules, and PC-to-PC remote technical support. If necessary, you can complete Product Return (RMA) forms and get information about repairs and spare or replacement parts. To get help immediately, contact a service office or your sales representative. Include your customer order number in your email or have it available before you call.

This manual contains proprietary information and may not be reproduced, disclosed, or used in whole or in part without the express written permission of Aerotech, Inc. Product names mentioned herein are used for identification purposes only and may be trademarks of their respective companies.

Copyright © 2021-2022, Aerotech, Inc., All rights reserved.



## Table of Contents

|   |           |
|---|-----------|
| <b>Automation1 XL2e High-Performance Linear Digital Drive</b> ..... | <b>1</b>  |
| Table of Contents .....   | 3         |
| List of Figures .....   | 5         |
| List of Tables .....  | 7         |
| EU Declaration of Conformity .....                                  | 9         |
| Agency Approvals .....  | 10        |
| Safety Procedures and Warnings .....                                | 11        |
| Handling and Storage .....  | 13        |
| Installation Overview .....   | 14        |
| <b>Chapter 1: XL2e Overview</b> .....                               | <b>15</b> |
| 1.1. Electrical Specifications .....                                | 18        |
| 1.2. Mechanical Specifications .....                                | 19        |
| 1.2.1. Mounting and Cooling .....                                   | 19        |
| 1.2.2. Dimensions .....   | 20        |
| 1.3. Environmental Specifications .....                             | 22        |
| 1.4. Drive and Software Compatibility .....                         | 23        |
| <b>Chapter 2: Installation and Configuration</b> .....              | <b>25</b> |
| 2.1. Input Power Connections .....                                  | 25        |
| 2.1.1. Control Supply Connector .....                               | 25        |
| 2.1.2. Motor Supply Connector .....                                 | 26        |
| 2.2. Motor Power Output Connector .....                             | 27        |
| 2.2.1. Brushless Motor Connections .....                            | 28        |
| 2.2.1.1. Brushless Motor Powered Motor and Feedback Phasing .....   | 29        |
| 2.2.1.2. Brushless Motor Unpowered Motor and Feedback Phasing ..... | 30        |
| 2.2.2. DC Brush Motor Connections .....                             | 31        |
| 2.2.2.1. DC Brush Motor Phasing .....                               | 31        |
| 2.2.3. Stepper Motor Connections .....                              | 32        |
| 2.2.3.1. Stepper Motor Phasing .....                                | 32        |
| 2.2.4. Three Phase Stepper Motor Connections .....                  | 33        |
| 2.2.4.1. Stepper Motor Phasing .....                                | 33        |
| 2.3. Feedback Connector .....                                       | 34        |
| 2.3.1. Primary Encoder Inputs .....                                 | 35        |
| 2.3.1.1. Square Wave Encoder (Primary) .....                        | 36        |
| 2.3.1.2. Absolute Encoder (Primary) .....                           | 37        |
| 2.3.1.3. Sine Wave Encoder (Primary) [-MX2/-MX3 Option] .....       | 38        |
| 2.3.1.4. Encoder Phasing .....                                      | 39        |
| 2.3.2. Hall-Effect Inputs .....                                     | 40        |
| 2.3.3. Thermistor Input .....                                       | 41        |
| 2.3.4. Encoder Fault Input .....                                    | 42        |
| 2.3.5. End of Travel and Home Limit Inputs .....                    | 43        |
| 2.3.5.1. End of Travel and Home Limit Phasing .....                 | 45        |
| 2.3.6. Brake Outputs .....  | 46        |
| 2.4. Safe Torque Off Input (STO) .....                              | 47        |
| 2.4.1. STO Standards .....  | 49        |
| 2.4.2. STO Functional Description .....                             | 50        |
| 2.4.3. STO Startup Validation Testing .....                         | 51        |
| 2.4.4. STO Diagnostics .....  | 52        |
| 2.5. HyperWire Interface .....                                      | 53        |
| 2.6. Sync Port .....  | 54        |
| 2.7. System Interconnection .....                                   | 55        |
| 2.8. PC Configuration and Operation Information .....               | 57        |
| <b>Chapter 3: -EB1 I/O Option Board</b> .....                       | <b>59</b> |
| 3.1. PSO Interface [-EB1] .....                                     | 60        |
| 3.2. Auxiliary Encoder Input [-EB1] .....                           | 62        |
| 3.2.1. Square Wave Encoder (Auxiliary) .....                        | 63        |
| 3.2.2. Absolute Encoder (Auxiliary) .....                           | 64        |

|  |           |
|--|-----------|
| 3.2.3. Sine Wave Encoder (Auxiliary) [-MX3 Option] ..... | 65        |
| 3.3. Analog I/O [-EB1] .....                             | 67        |
| 3.3.1. Analog Output 0 [-EB1] .....                      | 68        |
| 3.3.2. Analog Input (Differential) [-EB1] .....          | 69        |
| 3.4. Digital Outputs [-EB1] .....                        | 70        |
| 3.5. Digital Inputs [-EB1] .....                         | 73        |
| <b>Chapter 4: Cables and Accessories .....</b>           | <b>75</b> |
| 4.1. DIN Rail Mounting .....                             | 76        |
| 4.2. Joystick Interface .....                            | 77        |
| 4.3. Handwheel Interface .....                           | 78        |
| <b>Chapter 5: Maintenance .....</b>                      | <b>79</b> |
| 5.1. Preventative Maintenance .....                      | 80        |
| 5.2. Fuse Specifications .....                           | 81        |
| <b>Appendix A: Warranty and Field Service .....</b>      | <b>83</b> |
| <b>Appendix B: Revision History .....</b>                | <b>85</b> |
| <b>Index .....</b>                                       | <b>87</b> |

## List of Figures

|              |   |    |
|--------------|---|----|
| Figure 1-1:  | XL2e High-Performance Linear Digital Drive .....                        | 15 |
| Figure 1-2:  | Functional Diagram .....  | 17 |
| Figure 1-3:  | Dimensions .....  | 20 |
| Figure 1-4:  | Dimensions [-EB1] .....   | 21 |
| Figure 2-1:  | Control Supply Connections .....  | 25 |
| Figure 2-2:  | Motor Supply Connections .....  | 26 |
| Figure 2-3:  | Brushless Motor Configuration .....                                     | 28 |
| Figure 2-4:  | Positive Motor Direction .....  | 29 |
| Figure 2-5:  | Encoder and Hall Signal Diagnostics .....                               | 29 |
| Figure 2-6:  | Brushless Motor Phasing Oscilloscope Example .....                      | 30 |
| Figure 2-7:  | Brushless Motor Phasing Goal .....                                      | 30 |
| Figure 2-8:  | DC Brush Motor Configuration .....                                      | 31 |
| Figure 2-9:  | Positive Motor Direction .....  | 31 |
| Figure 2-10: | Stepper Motor Configuration .....                                       | 32 |
| Figure 2-11: | Positive Motor Direction .....  | 32 |
| Figure 2-12: | Three Phase Stepper Motor Configuration .....                           | 33 |
| Figure 2-13: | Positive Motor Direction .....  | 33 |
| Figure 2-14: | Square Wave Encoder Schematic (Feedback Connector) .....                | 36 |
| Figure 2-15: | Absolute Encoder Schematic (Feedback Connector) .....                   | 37 |
| Figure 2-16: | Sine Wave Encoder Phasing Reference Diagram .....                       | 38 |
| Figure 2-17: | Encoder Phasing Reference Diagram (Standard) .....                      | 39 |
| Figure 2-18: | Position Feedback in the Diagnostic Display .....                       | 39 |
| Figure 2-19: | Hall-Effect Inputs Schematic (Feedback Connector) .....                 | 40 |
| Figure 2-20: | Thermistor Input Schematic (Feedback Connector) .....                   | 41 |
| Figure 2-21: | Encoder Fault Input Schematic (Feedback Connector) .....                | 42 |
| Figure 2-22: | End of Travel and Home Limit Input Connections .....                    | 44 |
| Figure 2-23: | End of Travel and Home Limit Input Schematic (Feedback Connector) ..... | 44 |
| Figure 2-24: | End of Travel and Home Limit Input Diagnostic Display .....             | 45 |
| Figure 2-25: | Brake Connected to the 25-Pin Feedback Connector (Typical) .....        | 46 |
| Figure 2-26: | Typical STO Configuration .....   | 48 |
| Figure 2-27: | STO Timing .....  | 52 |
| Figure 2-28: | System Wiring Drawing (Best Practice) .....                             | 55 |
| Figure 2-29: | System Interconnection Drawing (Best Practice) .....                    | 56 |
| Figure 3-1:  | XL2e with -EB1 I/O Option Board Connectors .....                        | 59 |
| Figure 3-2:  | PSO Output Sources Current .....  | 61 |
| Figure 3-3:  | PSO Output Sinks Current .....  | 61 |
| Figure 3-4:  | PSO TTL Outputs Schematic .....   | 61 |
| Figure 3-5:  | Square Wave Encoder Interface (Aux Connector) .....                     | 63 |
| Figure 3-6:  | Absolute Encoder Schematic (Auxiliary Encoder Connector) .....          | 64 |
| Figure 3-7:  | Sine Wave Encoder Phasing Reference Diagram .....                       | 65 |
| Figure 3-8:  | Sine Wave Encoder Schematic (Aux Connector) .....                       | 66 |
| Figure 3-9:  | Analog Output Schematic [-EB1] .....                                    | 68 |
| Figure 3-10: | Analog Input Schematic [-EB1] .....                                     | 69 |
| Figure 3-11: | Digital Outputs Schematic [-EB1] .....                                  | 71 |
| Figure 3-12: | Digital Outputs Connected in Current Sourcing Mode [-EB1] .....         | 72 |
| Figure 3-13: | Digital Outputs Connected in Current Sinking Mode [-EB1] .....          | 72 |
| Figure 3-14: | Digital Inputs Schematic [-EB1] .....                                   | 73 |
| Figure 3-15: | Digital Inputs Connected to Current Sourcing (PNP) Devices [-EB1] ..... | 74 |

---

|   |    |
|---|----|
| Figure 3-16: Digital Inputs Connected to Current Sinking (NPN) Devices [-EB1] ..... | 74 |
| Figure 4-1: Din Rail Clip Dimensions .....  | 76 |
| Figure 4-2: Two Axis Joystick Interface .....                                       | 77 |
| Figure 4-3: Handwheel Interconnection to the Aux Connector .....                    | 78 |

## List of Tables

|             |  |    |
|-------------|--|----|
| Table 1-1:  | Feature Summary .....  | 16 |
| Table 1-2:  | Linear Amplifier Specifications .....                                      | 18 |
| Table 1-3:  | Mounting Specifications .....  | 19 |
| Table 1-4:  | Environmental Specifications .....   | 22 |
| Table 1-5:  | Drive and Software Compatibility .....                                     | 23 |
| Table 2-1:  | Control Supply Connector Wiring Specifications .....                       | 25 |
| Table 2-2:  | Mating Connector Part Numbers for the Control Supply Connector .....       | 25 |
| Table 2-3:  | Motor Supply Connector Wiring Specifications .....                         | 26 |
| Table 2-4:  | Mating Connector Part Numbers for the Motor Supply Connector .....         | 26 |
| Table 2-5:  | Motor Power Output Connector Pinout .....                                  | 27 |
| Table 2-6:  | Mating Connector Part Numbers for the Motor Power Output Connector .....   | 27 |
| Table 2-7:  | Wire Colors for Aerotech-Supplied Brushless Motor Cables .....             | 28 |
| Table 2-8:  | Hall Signal Diagnostics .....  | 29 |
| Table 2-9:  | Wire Colors for Aerotech-Supplied DC Brush Motor Cables .....              | 31 |
| Table 2-10: | Wire Colors for Aerotech-Supplied Stepper Motor Cables .....               | 32 |
| Table 2-11: | Feedback Connector Pinout .....  | 34 |
| Table 2-12: | Mating Connector Part Numbers for the Feedback Connector .....             | 34 |
| Table 2-13: | Multiplier Options .....   | 35 |
| Table 2-14: | Primary Encoder Input Pins on the Feedback Connector .....                 | 35 |
| Table 2-15: | Square Wave Encoder Specifications .....                                   | 36 |
| Table 2-16: | Sine Wave Encoder Specifications .....                                     | 38 |
| Table 2-17: | Hall-Effect Feedback Pins on the Feedback Connector .....                  | 40 |
| Table 2-18: | Thermistor Input Pin on the Feedback Connector .....                       | 41 |
| Table 2-19: | Encoder Fault Input Pin on the Feedback Connector .....                    | 42 |
| Table 2-20: | End of Travel and Home Limit Pins on the Feedback Connector .....          | 43 |
| Table 2-21: | Brake Output Pins on the Feedback Connector .....                          | 46 |
| Table 2-22: | Brake Control Specifications .....   | 46 |
| Table 2-23: | STO Connector Pinout .....   | 47 |
| Table 2-24: | Mating Connector Part Numbers for the STO Connector .....                  | 47 |
| Table 2-25: | STO Electrical Specifications .....  | 48 |
| Table 2-26: | STO Standards .....  | 49 |
| Table 2-27: | STO Standards Data .....   | 49 |
| Table 2-28: | STO Signal Delay .....   | 51 |
| Table 2-29: | Motor Function Relative to STO Input State .....                           | 51 |
| Table 2-30: | STO Timing .....   | 52 |
| Table 2-31: | HyperWire Card Part Number .....   | 53 |
| Table 2-32: | HyperWire Cable Part Numbers .....   | 53 |
| Table 2-33: | Sync-Related Functions .....   | 54 |
| Table 2-34: | Sync Port Cables .....   | 54 |
| Table 3-1:  | PSO Specifications [-EB1] .....  | 60 |
| Table 3-2:  | PSO Interface Connector Pinout [-EB1] .....                                | 60 |
| Table 3-3:  | Mating Connector Part Numbers for the PSO Interface Connector [-EB1] ..... | 60 |
| Table 3-4:  | Auxiliary Encoder Connector Pinout .....                                   | 62 |
| Table 3-5:  | Mating Connector Part Numbers for the AUX Connector .....                  | 62 |
| Table 3-6:  | Square Wave Encoder Specifications .....                                   | 63 |
| Table 3-7:  | Sine Wave Encoder Specifications .....                                     | 65 |
| Table 3-8:  | Analog I/O Connector Pinout [-EB1] .....                                   | 67 |
| Table 3-9:  | Mating Connector Part Numbers for the Analog I/O Connector [-EB1] .....    | 67 |

|             |   |    |
|-------------|---|----|
| Table 3-10: | Analog Output Specifications [-EB1]                                   | 68 |
| Table 3-11: | Analog Output Pins on the Analog I/O Connector [-EB1]                 | 68 |
| Table 3-12: | Differential Analog Input Specifications [-EB1]                       | 69 |
| Table 3-13: | Analog Input Pins on the Analog I/O Connector [-EB1]                  | 69 |
| Table 3-14: | Digital Output Specifications [-EB1]                                  | 70 |
| Table 3-15: | Digital Output Connector Pinout [-EB1]                                | 70 |
| Table 3-16: | Mating Connector Part Numbers for the Digital Output Connector [-EB1] | 70 |
| Table 3-17: | Digital Input Specifications [-EB1]                                   | 73 |
| Table 3-18: | Digital Input Connector Pinout [-EB1]                                 | 73 |
| Table 3-19: | Mating Connector Part Numbers for the Digital Input Connector [-EB1]  | 73 |
| Table 4-1:  | Standard Interconnection Cables                                       | 75 |
| Table 4-2:  | Mounting Parts  | 76 |
| Table 5-1:  | LED Description   | 79 |
| Table 5-2:  | Troubleshooting   | 79 |
| Table 5-3:  | Preventative Maintenance  | 80 |
| Table 5-4:  | Control Board Fuse Specifications                                     | 81 |



### EU Declaration of Conformity

**Manufacturer** Aerotech, Inc.  
**Address** 101 Zeta Drive  
 Pittsburgh, PA 15238-2811  
 USA  
**Product** XL2e  
**Model/Types** All


This is to certify that the aforementioned product is in accordance with the applicable requirements of the following directive(s):

|             |                                     |
|-------------|-------------------------------------|
| 2014/30/EU  | Electromagnetic Compatibility (EMC) |
| 2014/35/EU  | Low Voltage Directive               |
| 2006/42/EC  | Machinery Directive                 |
| 2011/65/EU  | RoHS 2 Directive                    |
| EU 2015/863 | Amendment RoHS 3 Directive          |


and has been designed to be in conformity with the applicable requirements of the following standard(s) when installed and used in accordance with the manufacturer's supplied installation instructions.

|                         |  |
|-------------------------|--|
| EN 61010-1:2010/A1:2016 | Safety Requirements for Electrical Equipment |
| EN 61800-3:2017         | EMC Requirements for Power Drives            |
| IEC 61800-5-1:2016      | Electrical Safety for Power Drive Systems    |
| IEC 61800-5-2:2016      | Functional Safety for Power Drive Systems    |
| EN 55011/55032:2015     | Conducted and Radiated Emissions             |

**Authorized Representative**

 / Simon Smith, European Director  
 Aerotech Ltd  
 The Old Brick Kiln, Ramsdell, Tadley  
 Hampshire RG26 5PR  
 UK

**Engineer Verifying Compliance**

 / Alex Weibel  
 Aerotech, Inc.  
 101 Zeta Drive  
 Pittsburgh, PA 15238-2811

**Date**

USA  
 1/28/2022



## Agency Approvals

**Approval:** CUS NRTL  
**Approving Agency:** TÜV SÜD America Inc.  
**Certificate #:**  
**Standards:**

CAN/CSA-C22.2 No. 61010-1:2012,  
EN 61010-1:2010/A1:2016,  
UL 61010-1:2012

**Approval:** Safety Components (STO)  
**Approving Agency:** TÜV SÜD  
**Certificate #:** Z10 068995 0030 Rev. 00  
**Standards:** EN ISO 13849-1:2015 (up to PL e),  
IEC 61508-1:2010 (up to SIL3),  
IEC 61508-2:2010 (up to SIL3),  
IEC 61800-5-2:2016,  
IEC 62061:2005 (up to SILCL3),  
IEC 62061:2005/AMD1:2012 (up to SILCL3),  
IEC 62061:2005/AMD2:2015 (up to SILCL3)

Visit <https://www.tuev-sued.de/product-testing/certificates> to view Aerotech's TÜV SÜD certificates. Type the certificate number listed above in the search bar or type "Aerotech" for a list of all Aerotech certificates.

PENDING

## Safety Procedures and Warnings



**IMPORTANT:** This manual tells you how to carefully and correctly use and operate the drive.

- Read all parts of this manual before you install or operate the drive or before you do maintenance to your system.
- To prevent injury to you and damage to the equipment, obey the precautions in this manual.
- All specifications and illustrations are for reference only and were complete and accurate as of the release of this manual. To find the newest information about this product, refer to [www.aerotech.com](http://www.aerotech.com).

If you do not understand the information in this manual, contact Aerotech Global Technical Support.



**IMPORTANT:** This product has been designed for light industrial manufacturing or laboratory environments. If the product is used in a manner not specified by the manufacturer:

- The protection provided by the equipment could be impaired.
- The life expectancy of the product could be decreased.

Safety notes and symbols are placed throughout this manual to warn you of the potential risks at the moment of the safety note or if you fail to obey the safety note.



The voltage can cause shock, burn, or death.



You are at risk of physical injury.  
You could damage the drive.



A surface can be hot enough to burn you.



Your actions, the temperature of the system, or the condition of the atmosphere that surround the system could start a fire.



Components are sensitive to electrostatic discharge.



Unsecured cables could cause you to:

- trip and fall
- drag the product off of its mounting location
- damage the cable connections.



A blue circle symbol is an action or tip that you should obey. Some examples include:



- General tip
- Read the manual/section
- Wear protective safety equipment (eye protection, ear protection, gloves)
- If applicable, do not lift unassisted

**DANGER:** To decrease the risk of electrical shock, injury, death, and damage to the equipment, obey the precautions that follow.



1. Before you do maintenance to the equipment, disconnect the electrical power.
2. Restrict access to the drive when it is connected to a power source.
3. Do not connect or disconnect electrical components, wires, and cables while this product is connected to a power source.
4. Wait at least one (1) minute after removing the power supply before doing maintenance or an inspection. Otherwise, there is the danger of electric shock.
5. Supply each operator with the necessary protection from live electrical circuits.
6. Make sure that all components are grounded correctly and that they obey the local electrical safety requirements.
7. Install the necessary precautions to supply safety and protection to the operator.



**DANGER:** System travel can cause crush, shear, or pinch injuries. Restrict access to all motor and stage parts while your system is connected to a power source.



**WARNING:** To prevent damage to the equipment and decrease the risk of electrical shock and injury, obey the precautions that follow.

1. Make sure that all system cables are correctly attached and positioned.
2. Do not use the cables or the connectors to lift or move this product.
3. Use this product only in environments and operating conditions that are approved in this manual.
4. Only trained operators should operate this equipment.

## Handling and Storage

### Unpacking the Chassis



**IMPORTANT:** All electronic equipment and instrumentation is wrapped in antistatic material and packaged with desiccant. Ensure that the antistatic material is not damaged during unpacking.

Inspect the shipping container for any evidence of shipping damage. If any damage exists, notify the shipping carrier immediately.

Remove the packing list from the shipping container. Make sure that all the items specified on the packing list are contained within the package.

The documentation for the drive is on the included installation device. The documents include manuals, interconnection drawings, and other documentation pertaining to the system. Save this information for future reference. Additional information about the system is provided on the Serial and Power labels that are placed on the chassis.

The system serial number label contains important information such as the:

- Customer order number (please provide this number when requesting product support)
- Drawing number
- System part number

### Handling



**IMPORTANT:** It is the responsibility of the customer to safely and carefully lift and move the drive.

- Be careful when you move or transport the drive.
- Refer to [Section 1.2. Mechanical Specifications](#) for dimensions and weight specifications.
- Retain the shipping materials for future use.
- Transport or store the drive in its protective packaging.



**WARNING: Electrostatic Discharge (ESD) Sensitive Components!**

You could damage the power supply or drives if you fail to observe the correct ESD practices.

Wear an ESD wrist strap when you handle, install, or do service to the system assembly.

### Storage


Store the drive in the original shipping container. If the original packaging included ESD protective packaging, make sure to store the drive in it. The storage location must be dry, free of dust, free of vibrations, and flat.

Refer to [Section 1.3. Environmental Specifications](#)

## Installation Overview

This image shows the order in which to make connections and settings that are typical to the XL2e. If a custom interconnect drawing was supplied with your system, that drawing is on your Storage Device and shows as a line item on your Sales Order in the Integration section.

**Figure 1: Installation Connection Overview**




|   |   |                                |
|---|---|--------------------------------|
| 1 | Connect the motor to the amplifier Motor Output connector.                                | <a href="#">Section 2.2.</a>   |
| 1 | Connect the motor to the amplifier Feedback connector.                                    | <a href="#">Section 2.3.</a>   |
| 2 | Connect a PC or drive-based controller HyperWire port to the HyperWire In port.           | <a href="#">Section 2.5.</a>   |
| 3 | Connect additional I/O as required by your application (if you purchased the I/O option). | <a href="#">Chapter 3</a>      |
| 4 | Connect the Safe Torque Off (STO).  | <a href="#">Section 2.4.</a>   |
| 5 | Connect the power supply to the Control Supply connector.                                 | <a href="#">Section 2.1.1.</a> |
| 6 | Connect the motor power to the Motor Supply connector.                                    | <a href="#">Section 2.1.2.</a> |

# Chapter 1: XL2e Overview

The XL2e is a high-performance linear amplifier designed for motion control applications that require the highest positioning accuracy and lowest generated noise. Refer to [Table 1-1](#) for a complete list of features and options.

**Figure 1-1: XL2e High-Performance Linear Digital Drive**




**Table 1-1: Feature Summary**

| <b>Standard Features</b>  |  |
|---|--|
| <ul style="list-style-type: none"> <li>• 24 VDC control supply input (Section 2.1.1.)</li> <li>• <math>\pm 5</math> to <math>\pm 48</math> VDC bipolar motor supply inputs (Section 2.1.2.)</li> <li>• Line driver square wave quadrature encoder input for position and velocity feedback (Section 2.3.1.)</li> <li>• Absolute Encoder support (Section 2.3.1.2.)</li> <li>• One fail-safe brake output (Section 2.3.6.)</li> <li>• Two STO sense inputs (Section 2.4.)</li> </ul> |  |
| <b>Options</b>  |  |
| <b>Peak Current (Section 1.1.)</b>  |  |
| -10   | 10 A Peak, 5 A Continuous Current  |
| <b>Expansion Board (Chapter 3)</b>  |  |
| -EB0  | No expansion board   |
| -EB1  | I/O expansion board <ul style="list-style-type: none"> <li>• 16-bit analog output (<math>\pm 10</math> V)</li> <li>• 16-bit differential analog input (<math>\pm 10</math> V)</li> <li>• 8 digital logic inputs (5 - 24 VDC), can be connected to current sourcing or sinking devices</li> <li>• 8 digital logic outputs (5 - 24 VDC), can be connected as current sourcing or sinking</li> <li>• Digital logic laser firing (PSO) output</li> </ul> |
| <b>PSO (Section 3.1.)</b>   |  |
| -PSO1   | One-axis PSO firing (includes One-axis Part-Speed PSO)   |
| -PSO2   | Two-axis PSO firing (includes Two-axis Part-Speed PSO)   |
| -PSO3   | Three-axis PSO firing (includes Three-axis Part-Speed PSO)   |
| -PSO5   | Two-axis Part-Speed PSO firing, which uses the PSO firing circuit based off of the commanded vector velocity of up to 2 axes (includes One-Axis PSO).  |
| -PSO6   | Three-axis Part-Speed PSO firing, which uses the PSO firing circuit based off of the commanded vector velocity of 3 or more axes (includes One-Axis PSO).  |
| NOTE: Requires -EB1 option to generate a PSO output pulse   |  |
| <b>Multiplier (Section 2.3.1.3.)</b>  |  |
| -MX0  | No encoder multiplier  |
| -MX2  | Interpolation circuit allowing for analog sine wave input on the primary encoder channel with an interpolation factor of 65,536.   |
| -MX3  | Interpolation circuit allowing for analog sine wave input on the primary encoder channel with an interpolation factor of 65,536 and an auxiliary encoder channel with an interpolation factor of 16,384.   |
| <b>Version</b>  |  |
| -DEFAULT  | Firmware Matches Software Line   |
| -LEGACY   | Legacy Firmware Version X.XX.XXX   |



The block diagram that follows shows a summary of the connector signals.

**Figure 1-2: Functional Diagram**



## 1.1. Electrical Specifications

**Table 1-2: Linear Amplifier Specifications**

|  |                            | XL2e   |                     |                     |                     |                     |
|--|----------------------------|--|---------------------|---------------------|---------------------|---------------------|
| Motor Supply   | Input Voltage              | ±5 VDC to ±48 VDC  |                     |                     |                     |                     |
|  | Input Current (continuous) | 5 A  |                     |                     |                     |                     |
|  | Input Current              | 10 A   |                     |                     |                     |                     |
| Control Supply   | Input Voltage              | 24 VDC   |                     |                     |                     |                     |
|  | Input Current              | 2 A max, 0.75 A typical without brake  |                     |                     |                     |                     |
| Output Voltage (maximum)   |                            | ±48 VDC  |                     |                     |                     |                     |
| Peak Output Current (1 second) <sup>(1)</sup>  |                            | 10 A <sub>pk</sub>   |                     |                     |                     |                     |
| Continuous Output Current <sup>(2, 3)</sup>  |                            | ±48 Bus  | ±40 Bus             | ±24 Bus             | ±20 Bus             | ±12 Bus             |
| Stationary AC or DC motor  |                            | 1.3 A <sub>pk</sub>  | 1.6 A <sub>pk</sub> | 2.7 A <sub>pk</sub> | 3.3 A <sub>pk</sub> | 5.0 A <sub>pk</sub> |
| AC motor that is in motion   |                            | 1.7 A <sub>pk</sub>  | 2.2 A <sub>pk</sub> | 3.8 A <sub>pk</sub> | 4.5 A <sub>pk</sub> | 5.0 A <sub>pk</sub> |
| Maximum Continuous Total Power Dissipation <sup>(3)</sup>  |                            | 180 W  |                     |                     |                     |                     |
| Peak Amplifier Power Dissipation per phase <sup>(4)</sup>  |                            | 400 W  |                     |                     |                     |                     |
| Effective Heatsink Thermal Resistance  |                            | 0.25°C/W   |                     |                     |                     |                     |
| Maximum Transistor Temperature   |                            | 75°C   |                     |                     |                     |                     |
| Time to reach maximum temperature at maximum continuous power  |                            | 8 minutes  |                     |                     |                     |                     |
| Power Amplifier Bandwidth  |                            | 2500 Hz maximum (software selectable)  |                     |                     |                     |                     |
| Modes of operation   |                            | Brushless, Brush, Stepper  |                     |                     |                     |                     |
| Protection Features  |                            | Peak current limit; Over temperature; RMS current limit; Control power supply under voltage; Dynamic power limit (SOA) |                     |                     |                     |                     |
| <p>(1) This specification depends on the motor supply voltage, the motor speed, and motor resistance. Contact an Aerotech sales engineer for more information.</p> <p>(2) This specification assumes that an AC or DC motor type with a 0 Ω winding resistance is used.</p> <p>(3) The specification will be lower when the ambient temperature exceeds 25°C.</p> <p>(4) The amplifier will limit peak power to protect itself from damage. The Amplifier Status internal signal in the Data Visualizer shows the current state of the power limiting circuitry.</p> |                            |  |                     |                     |                     |                     |

## 1.2. Mechanical Specifications

### 1.2.1. Mounting and Cooling

Install the drive in an IP54 compliant enclosure to comply with safety standards. Make sure that there is sufficient clearance surrounding the drive for free airflow and for the cables and connections.

**Table 1-3: Mounting Specifications**

|                             |            | XL2e  |
|-----------------------------|------------|---|
| Customer-Supplied Enclosure |            | IP54 Compliant  |
|                             |            | For DIN Rail Mounting,<br>refer to <a href="#">Section 4.1. DIN Rail Mounting</a> |
| Weight                      |            | ~1.0 kg   |
| Mounting Hardware           |            | M3.5 [#6] screws (four locations, not included)                                   |
| Mounting Orientation        |            | Vertical (typical)  |
| Dimensions                  |            | Refer to <a href="#">Section 1.2.2. Dimensions</a>                                |
| Minimum Clearance           | Airflow    | ~25 mm  |
|                             | Connectors | ~100 mm   |
| Operating Temperature       |            | Refer to <a href="#">Section 1.3. Environmental Specifications</a>                |

### 1.2.2. Dimensions

Figure 1-3: Dimensions





Figure 1-4: Dimensions [-EB1]



### 1.3. Environmental Specifications

The environmental specifications are listed below.

**Table 1-4: Environmental Specifications**

|                                |   |
|--------------------------------|---|
| <b>Ambient Temperature</b>     | Operating: 0° to 40°C (32° to 104° F)   |
|                                | Storage: -30° to 85°C (-22° to 185° F)  |
| <b>Humidity Non-condensing</b> | The maximum relative humidity is 80% for temperatures that are less than 31°C and decreases linearly to 50% relative humidity at 40°C.          |
| <b>Operating Altitude</b>      | 0 m to 2,000 m (0 ft to 6,562 ft) above sea level.<br>If you must operate this product above 2,000 m or below sea level, contact Aerotech, Inc. |
| <b>Pollution</b>               | Pollution Degree 2<br>Typically only nonconductive pollution occurs.  |
| <b>Operation</b>               | Use only indoors  |

## 1.4. Drive and Software Compatibility

This table shows the available drives and which version of the software first supported each drive. In the **Last Software Version** column, drives that show a specific version number are not supported after that version.

**Table 1-5: Drive and Software Compatibility**

| Drive Type | First Software Version | Last Software Version |
|------------|------------------------|-----------------------|
| XL2e       | 2.0.0                  | Current               |

*This page intentionally left blank.*



## Chapter 2: Installation and Configuration

The sections in this chapter include details on how to set up the electrical and safety components of your system. Obey all safety warnings, including those in [Safety Procedures and Warnings](#).

### 2.1. Input Power Connections

The drive has two DC input power connectors. One connector is for control power and the other connector is for motor power. For a full list of electrical specifications, refer to [Section 1.1](#). Refer to [Section 2.7](#) for a System Interconnection Drawing.


#### 2.1.1. Control Supply Connector

The Control Supply input supplies power to the communications and logic circuitry of the drive. The **+24V** input is connected to an internal fuse. Refer to [Table 5-4](#) for the internal fuse value and part number. For an isolated DC supply, connect **0V** to protective ground at the supply. Use twisted pair wiring to minimize radiated noise emissions (refer to [Figure 2-1](#)).



**IMPORTANT:** Refer to local electrical safety requirements to correctly size external system wires.

**Figure 2-1: Control Supply Connections**



**Table 2-1: Control Supply Connector Wiring Specifications**

| Pin   | Description  | Recommended Wire Size          |
|-------|--|--------------------------------|
| +24 V | 24 VDC ( $\pm 10\%$ ) Control Power Input<br>(2 A max, 0.75 A typical without brake) | 0.34 mm <sup>2</sup> (#22 AWG) |
| 0 V   | Control Power Common Input   | 0.34 mm <sup>2</sup> (#22 AWG) |
|       | Protective Ground  | 0.34 mm <sup>2</sup> (#22 AWG) |

**Table 2-2: Mating Connector Part Numbers for the Control Supply Connector**

| Type                 | Aerotech P/N | Third Party P/N | Screw Torque: N·m | Wire Size: mm <sup>2</sup> [AWG] |
|----------------------|--------------|-----------------|-------------------|----------------------------------|
| 3-Pin Terminal Block | ECK02456     | Phoenix 1839610 | 0.22 - 0.25       | 2.5 - 0.05 [14-30]               |


## 2.1.2. Motor Supply Connector

Motor power is applied to the **B+**, **B-**, and **RET** terminals of the Motor Supply connector. To improve thermal performance of the amplifier, you should use the lowest motor supply voltage that you need for your application. The **B+** and **B-** inputs are connected to internal fuses. Refer to [Table 5-4](#) for the internal fuse values and part numbers. For an isolated DC supply, connect **RET** to protective ground at the supply. Use twisted pair wiring to minimize radiated noise emissions (refer to [Figure 2-2](#)).



**IMPORTANT:** Refer to local electrical safety requirements to correctly size external system wires.

**Figure 2-2: Motor Supply Connections**



**Table 2-3: Motor Supply Connector Wiring Specifications**

| Pin | Description            | Recommended Wire Size         |
|-----|------------------------|-------------------------------|
| B+  | +DC Motor Supply Input | 0.5 mm <sup>2</sup> (#20 AWG) |
| RET | DC Motor Supply Return | 0.5 mm <sup>2</sup> (#20 AWG) |
| B-  | -DC Motor Supply Input | 0.5 mm <sup>2</sup> (#20 AWG) |
| ⊕   | Protective Ground      | 0.5 mm <sup>2</sup> (#20 AWG) |

**Table 2-4: Mating Connector Part Numbers for the Motor Supply Connector**

| Type                 | Aerotech P/N | Third Party P/N | Screw Torque: Nm | Wire Size: mm <sup>2</sup> [AWG] |
|----------------------|--------------|-----------------|------------------|----------------------------------|
| 8-Pin Terminal Block | ECK02625     | Phoenix 1839694 | 0.22 - 0.25      | 1.5 - 0.08 [16 - 28]             |

## 2.2. Motor Power Output Connector



**DANGER:** Before you do maintenance to the equipment, disconnect the electrical power. Wait at least one (1) minute after removing the power supply before doing maintenance or an inspection. Otherwise, there is the danger of electric shock.

The drive can be used to drive the following motor types:

- Brushless (refer to [Section 2.2.1.](#))
- DC Brush (refer to [Section 2.2.2.](#))
- Stepper (refer to [Section 2.2.3.](#))

For a complete list of electrical specifications, refer to [Section 1.1.](#)



**IMPORTANT:** Refer to local electrical safety requirements to correctly size external system wires.

The 8-pin terminal block style motor output connector is located on the front panel. The pinout for this connector is shown in [Table 2-5.](#)

**Table 2-5: Motor Power Output Connector Pinout**

| Pin | Description  | Recommended Wire Size         | Connector |
|-----|--|-------------------------------|-----------|
|     | Earth Ground to Motor  | 0.5 mm <sup>2</sup> (#20 AWG) |           |
| A   | Brushless Phase A Motor Lead<br>DC Brush +<br>Stepper        | 0.5 mm <sup>2</sup> (#20 AWG) |           |
| B   | Brushless Phase B Motor Lead<br>Stepper                      | 0.5 mm <sup>2</sup> (#20 AWG) |           |
| C   | Brushless Phase C Motor Lead<br>DC Brush -<br>Stepper Return | 0.5 mm <sup>2</sup> (#20 AWG) |           |


**Table 2-6: Mating Connector Part Numbers for the Motor Power Output Connector**

| Type                 | Aerotech P/N | Third Party P/N | Screw Torque: Nm | Wire Size: mm <sup>2</sup> [AWG] |
|----------------------|--------------|-----------------|------------------|----------------------------------|
| 8-Pin Terminal Block | ECK02625     | Phoenix 1839694 | 0.22 - 0.25      | 1.5 - 0.08 [16 - 28]             |

### 2.2.1. Brushless Motor Connections

The configuration in [Figure 2-3](#) shows a typical brushless motor connection.

**Figure 2-3: Brushless Motor Configuration**



**Table 2-7: Wire Colors for Aerotech-Supplied Brushless Motor Cables**

| Pin | Wire Color Set 1 <sup>(1)</sup>      | Wire Color Set 2      | Wire Color Set 3      | Wire Color Set 4      |
|-----|--------------------------------------|-----------------------|-----------------------|-----------------------|
| ⊕   | Green/Yellow & Shield <sup>(2)</sup> | Green/Yellow & Shield | Green/Yellow & Shield | Green/Yellow & Shield |
| A   | Black                                | Blue & Yellow         | Black #1              | Black & Brown         |
| B   | Red                                  | Red & Orange          | Black #2              | Red & Orange          |
| C   | White                                | White & Brown         | Black #3              | Violet & Blue         |

(1) Wire Color Set #1 is the wire set typically used by Aerotech.

(2) "&" indicates two wires (Red & Orange); "/" indicates a single wire (Green/White).

Brushless motors are commutated electronically by the controller. The use of Hall effect devices for commutation is recommended.

The controller requires that the Back-EMF of each motor phase be aligned with the corresponding Hall-effect signal. To ensure proper alignment, motor, Hall, and encoder connections should be verified using one of the following methods: *powered*, through the use of a test program; or *unpowered* using an oscilloscope. Both methods will identify the A, B, and C Hall/motor lead sets and indicate the correct connections to the controller. Refer to [Section 2.2.1.1.](#) for powered motor phasing or [Section 2.2.1.2.](#) for unpowered motor and feedback phasing.

For Aerotech-supplied systems, the motor, encoder and Hall sensors are correctly configured and connection adjustments are not necessary.


**2.2.1.1. Brushless Motor Powered Motor and Feedback Phasing**

Observe the state of the encoder and Hall-effect device signals in the Diagnostics section of the Status Utility.


**Table 2-8: Hall Signal Diagnostics**

| Hall-Signal Status | Definition        |
|--------------------|-------------------|
| --                 | 0 V or logic low  |
| ON                 | 5 V or logic high |

**Figure 2-4: Positive Motor Direction**




**Figure 2-5: Encoder and Hall Signal Diagnostics**



**2.2.1.2. Brushless Motor Unpowered Motor and Feedback Phasing**


Disconnect the motor from the controller and connect the motor in the test configuration shown in Figure 2-6. This method will require a two-channel oscilloscope, a 5V power supply, and six resistors (10,000 ohm, 1/4 watt). All measurements should be made with the probe common of each channel of the oscilloscope connected to a neutral reference test point (TP4, shown in Figure 2-6). Wave forms are shown while moving the motor in the positive direction.

**Figure 2-6: Brushless Motor Phasing Oscilloscope Example**



With the designations of the motor and Hall leads of a third party motor determined, the motor can now be connected to an Aerotech system. Connect motor lead A to motor connector A, motor lead B to motor connector B, and motor lead C to motor connector C. Hall leads should also be connected to their respective feedback connector pins (Hall A lead to the Hall A feedback pin, Hall B to Hall B, and Hall C to Hall C). The motor is correctly phased when the Hall states align with the Back EMF as shown in Figure 2-7. Use the CommutationOffset parameter to correct for Hall signal misalignment.


**Figure 2-7: Brushless Motor Phasing Goal**



**2.2.2. DC Brush Motor Connections**

The configuration shown in Figure 2-8 is an example of a typical DC brush motor connection. Refer to Section 2.2.2.1. for information on motor phasing.

**Figure 2-8: DC Brush Motor Configuration**



**Table 2-9: Wire Colors for Aerotech-Supplied DC Brush Motor Cables**

| Pin | Wire Color Set 1 <sup>(1)</sup>       | Wire Color Set 2      | Wire Color Set 3      |
|-----|---------------------------------------|-----------------------|-----------------------|
| RET | Green & White & Shield <sup>(2)</sup> | Green/Yellow & Shield | Green/Yellow & Shield |
| A   | Red & Orange                          | Red                   | Red & Orange          |
| C   | Yellow & Blue                         | Black                 | Yellow & Blue         |


(1) Wire Color Set #1 is the typical wire set used by Aerotech.  
 (2) "&" (Red & Orange) indicates two wires; "/" (Green/White) indicates a single wire.

**2.2.2.1. DC Brush Motor Phasing**

A properly phased motor means that the positive motor lead should be connected to the ØA motor terminal and the negative motor lead should be connected to the ØC motor terminal. To determine if the motor is properly phased, connect a voltmeter to the motor leads of an un-powered motor:

1. Connect the positive lead of the voltmeter to the one of the motor terminals.
2. Connect the negative lead of the voltmeter to the other motor terminal.
3. Move or rotate the motor in the positive or clockwise (CW) direction by hand.

**Figure 2-9: Positive Motor Direction**



4. If the voltmeter indicates a negative value, swap the motor leads and move the motor by hand in the positive direction, again. When the voltmeter indicates a positive value, the motor leads have been identified.
5. Connect the motor lead from the positive lead of the voltmeter to the ØA motor terminal on the drive. Connect the motor lead from the negative lead of the voltmeter to the ØC motor terminal on the drive.


For Aerotech-supplied systems, the motor, encoder and Hall sensors are correctly configured and connection adjustments are not necessary.

### 2.2.3. Stepper Motor Connections

The configuration shown in Figure 2-10 is an example of a typical stepper motor connection. Refer to Section 2.2.3.1. for information on motor phasing.

In this case, the effective motor voltage is half of the applied bus voltage. For example, an 80 V motor bus supply is needed to get 40 V across the motor.

**Figure 2-10: Stepper Motor Configuration**



**Table 2-10: Wire Colors for Aerotech-Supplied Stepper Motor Cables**

| Pin | Wire Color Set 1 <sup>(1)</sup>      | Wire Color Set 2      |
|-----|--------------------------------------|-----------------------|
| ⊕   | Green/Yellow & Shield <sup>(2)</sup> | Green/Yellow & Shield |
| A   | Black                                | Brown                 |
| B   | Red                                  | Yellow                |
| C   | White                                | White & Red           |

(1) Wire Color Set #1 is the typical wire set used by Aerotech.  
 (2) "&" (Red & Orange) indicates two wires; "/" (Green/White) indicates a single wire.

#### 2.2.3.1. Stepper Motor Phasing


A stepper motor can be run with or without an encoder.

**Without an Encoder:** You do not need to phase the motor.

**With an Encoder:** Because the end of travel (EOT) limit inputs are relative to motor rotation, it is important to phase the motor.

Run a positive motion command. The motor is phased correctly if there is a positive scaling factor (determined by the ServoLoopSetup parameter) and the motor moves in a clockwise direction when you view the motor from the front mounting flange (Figure 2-11). If the motor moves in a counterclockwise direction, reverse the motor leads and re-run the command. After the motor has been phased, if you want to change the direction of positive motion, use the ReverseMotionDirection parameter.

**Figure 2-11: Positive Motor Direction**



For Aerotech-supplied systems, the motor, encoder and Hall sensors are correctly configured and connection adjustments are not necessary.




**2.2.4. Three Phase Stepper Motor Connections**



**IMPORTANT:** This feature is only supported in Automation1 software version 2.2.0. or later.

The configuration shown in Figure 2-12 is an example of a typical three phase stepper motor connection. Refer to Section 2.2.4.1. for information on motor phasing.

**Figure 2-12: Three Phase Stepper Motor Configuration**



**2.2.4.1. Stepper Motor Phasing**


A three phase stepper motor can be run with or without an encoder.

**Without an Encoder:** You do not need to phase the motor.

**With an Encoder:** Because the end of travel (EOT) limit inputs are relative to motor rotation, it is important to phase the motor.

Run a positive motion command. The motor is phased correctly if there is a positive scaling factor (determined by the ServoLoopSetup parameter) and the motor moves in a clockwise direction when you view the motor from the front mounting flange (Figure 2-13). If the motor moves in a counterclockwise direction, reverse the motor leads and re-run the command. After the motor has been phased, if you want to change the direction of positive motion, use the ReverseMotionDirection parameter.


**Figure 2-13: Positive Motor Direction**



## 2.3. Feedback Connector

The connector pin assignment is shown in [Table 2-11](#) with detailed connection information in the following sections.

**Table 2-11: Feedback Connector Pinout**

| Pin # | Description  | In/Out/Bi     | Connector  |
|-------|--|---------------|--|
| 1     | Reserved   | N/A           |  |
| 2     | Motor Over Temperature Thermistor                    | Input         |  |
| 3     | +5V Power <sup>(1)</sup>                             | Output        |  |
| 4     | Plug and Play Serial Data (for Aerotech stages only) | Bidirectional |  |
| 5     | Hall-Effect Sensor B (brushless motors only)         | Input         |  |
| 6     | Encoder Marker Reference Pulse -                     | Input         |  |
|       | Absolute Encoder Clock -                             | Output        |  |
| 7     | Encoder Marker Reference Pulse +                     | Input         |  |
|       | Absolute Encoder Clock +                             | Output        |  |
| 8     | Absolute Encoder Data -                              | Bidirectional |  |
| 9     | Reserved   | N/A           |  |
| 10    | Hall-Effect Sensor A (brushless motors only)         | Input         |  |
| 11    | Hall-Effect Sensor C (brushless motors only)         | Input         |  |
| 12    | Clockwise End of Travel Limit                        | Input         |  |
| 13    | Brake Output -                                       | Output        |  |
| 14    | Encoder Cosine +                                     | Input         |  |
| 15    | Encoder Cosine -                                     | Input         |  |
| 16    | +5V Power <sup>(1)</sup>                             | Output        |  |
| 17    | Encoder Sine +                                       | Input         |  |
| 18    | Encoder Sine -                                       | Input         |  |
| 19    | Absolute Encoder Data+                               | Bidirectional |  |
| 20    | Signal Common  | Output        |  |
| 21    | Signal Common  | Output        |  |
| 22    | Home Switch Input                                    | Input         |  |
| 23    | Encoder Fault Input                                  | Input         |  |
| 24    | Counterclockwise End of Travel Limit                 | Input         |  |
| 25    | Brake Output +                                       | Output        |  |

(1) The maximum combined current output is 500 mA.

**Table 2-12: Mating Connector Part Numbers for the Feedback Connector**

| Mating Connector   | Aerotech P/N | Third Party P/N     |
|--------------------|--------------|---------------------|
| 25-Pin D-Connector | ECK00101     | FCI DB25P064TXLF    |
| Backshell          | ECK00656     | Amphenol 17E-1726-2 |

### 2.3.1. Primary Encoder Inputs

The primary encoder inputs are accessible through the Feedback connector. Use the PrimaryFeedbackType parameter to configure the drive to accept an encoder signal type.

Square Wave encoder signals: [Section 2.3.1.1.](#)

Absolute encoder signals: [Section 2.3.1.2.](#)

Sine Wave encoder signals (as permitted by the multiplier option): [Section 2.3.1.3.](#)

Refer to [Section 2.3.1.4.](#) for encoder feedback phasing.

Refer to [Section 3.2.](#) for the auxiliary encoder input on the AUX connector.

**Table 2-13: Multiplier Options**

| Option | Primary Encoder Accepts...                                      | Auxiliary Encoder Accepts...                             |
|--------|---|--|
| -MX0   | Square Wave or Absolute encoders                                | Square Wave encoders                                     |
| -MX2   | Sine Wave (high performance), Square Wave, or Absolute encoders | Square Wave encoders                                     |
| -MX3   | Sine Wave (high performance), Square Wave, or Absolute encoders | Sine Wave (standard performance) or Square Wave encoders |



**IMPORTANT:** Physically isolate the encoder wiring from motor, AC power, and all other power wiring

**Table 2-14: Primary Encoder Input Pins on the Feedback Connector**

| Pin # | Description                      | In/Out/Bi     |
|-------|----------------------------------|---------------|
| 3     | +5V Power <sup>(1)</sup>         | Output        |
| 6     | Encoder Marker Reference Pulse - | Input         |
|       | Absolute Encoder Clock -         | Output        |
| 7     | Encoder Marker Reference Pulse + | Input         |
|       | Absolute Encoder Clock +         | Output        |
| 8     | Absolute Encoder Data -          | Bidirectional |
| 14    | Encoder Cosine +                 | Input         |
| 15    | Encoder Cosine -                 | Input         |
| 16    | +5V Power <sup>(1)</sup>         | Output        |
| 17    | Encoder Sine +                   | Input         |
| 18    | Encoder Sine -                   | Input         |
| 19    | Absolute Encoder Data+           | Bidirectional |
| 20    | Signal Common                    | Output        |
| 21    | Signal Common                    | Output        |

(1) The maximum combined current output is 500 mA.


**2.3.1.1. Square Wave Encoder (Primary)**

The drive accepts RS-422 square wave encoder signals. The drive will generate a feedback fault if it detects an invalid signal state caused by an open or shorted signal connection. Use twisted-pair wiring for the highest performance and noise immunity.

**Table 2-15: Square Wave Encoder Specifications**

| Specification          | Value  |
|------------------------|--|
| Encoder Frequency      | 10 MHz maximum (25 ns minimum edge separation) |
| x4 Quadrature Decoding | 40 million counts/sec                          |

**Figure 2-14: Square Wave Encoder Schematic (Feedback Connector)**




### 2.3.1.2. Absolute Encoder (Primary)

The drive retrieves absolute position data along with encoder fault information through a serial data stream from the absolute encoder. Use twisted-pair wiring for the highest performance and noise immunity. You cannot echo an absolute encoder signal.

Refer to [Figure 2-15](#) for the serial data stream interface.

Refer to the [Help file](#) for information on how to set up your EnDat or BiSS absolute encoder parameters.

**Figure 2-15: Absolute Encoder Schematic (Feedback Connector)**



**2.3.1.3. Sine Wave Encoder (Primary) [-MX2/-MX3 Option]**

The Sine Wave Encoder option provides higher positioning resolution by subdividing the fundamental output period of the encoder into smaller increments. The amount of subdivision is specified by the PrimaryEncoderMultiplicationFactor parameter. Use Encoder Tuning to adjust the value of the gain, offset, and phase balance controller parameters to get the best performance. For more information, refer to the [Help file](#).

High resolution or high-speed encoders can require increased bandwidth for correct operation. Use the High Speed Mode of the PrimaryEncoderMultiplierSetup parameter to enable the high bandwidth mode. Because this mode increases sensitivity to system noise, use it only if necessary. This option is only available on the Primary encoder input.


The drive can generate emulated encoder signals. These signals can be output on the Auxiliary Encoder (AUX) connector or used internally by the PSO. Refer to the EncoderDivider and PrimaryEmulatedQuadratureDivider parameters and the encoder output functions in the Help file for more information.

For the highest performance, use twisted pair double-shielded cable with the inner shield connected to signal common and the outer shield connected to frame ground. Do not join the inner and outer shields in the cable.

**Table 2-16: Sine Wave Encoder Specifications**

| Specification   | Value  |           |
|---|--|-----------|
|   | Primary                                      | Auxiliary |
| Input Frequency (max)   | 200 kHz, 2 MHz                               | 200 kHz   |
| Input Amplitude <sup>(1)</sup>                                    | 0.6 to 1.75 Vpk-pk                           |           |
| Interpolation Factor (max)  | -MX2   | 65,536    |
|   | -MX3   | 65,536    |
| -MX2/-MX3 Primary Encoder Channel Interpolation Latency           | 800 nsec (analog input to quadrature output) |           |
| Input Common Mode   | 1.5 to 3.5 VDC                               |           |
| <small>(1) Measured as SIN(+) - SIN(-) or COS(+) - COS(-)</small> |  |           |

**Figure 2-16: Sine Wave Encoder Phasing Reference Diagram**




**2.3.1.4. Encoder Phasing**

Incorrect encoder polarity will cause the system to fault when enabled or when a move command is issued. Figure 2-17 illustrates the proper encoder phasing for clockwise motor rotation (or positive forcer movement for linear motors). To verify, move the motor by hand in the CW (positive) direction while observing the position of the encoder in the diagnostics display (see Figure 2-18).


For dual loop systems, the velocity feedback encoder is displayed in the diagnostic display (Figure 2-18).

**Figure 2-17: Encoder Phasing Reference Diagram (Standard)**



**IMPORTANT:** Encoder manufacturers may refer to the encoder signals as A, B, and Z. The proper phase relationship between signals is shown in Figure 2-17.

**Figure 2-18: Position Feedback in the Diagnostic Display**



### 2.3.2. Hall-Effect Inputs

The Hall-effect switch inputs are recommended for AC brushless motor commutation but not absolutely required. The Hall-effect inputs accept 5 VDC level signals. Hall states (0,0,0) or (1,1,1) are invalid and will generate a "Hall Fault" axis fault.


Refer to [Section 2.2.1.1](#), for Hall-effect device phasing.

**Table 2-17: Hall-Effect Feedback Pins on the Feedback Connector**

| Pin # | Description                                  | In/Out/Bi |
|-------|--|-----------|
| 3     | +5V Power <sup>(1)</sup>                     | Output    |
| 5     | Hall-Effect Sensor B (brushless motors only) | Input     |
| 10    | Hall-Effect Sensor A (brushless motors only) | Input     |
| 11    | Hall-Effect Sensor C (brushless motors only) | Input     |
| 16    | +5V Power <sup>(1)</sup>                     | Output    |
| 20    | Signal Common                                | Output    |
| 21    | Signal Common                                | Output    |

(1) The maximum combined current output is 500 mA.

**Figure 2-19: Hall-Effect Inputs Schematic (Feedback Connector)**





### 2.3.3. Thermistor Input


The thermistor input is used to detect a motor over temperature condition by using a positive temperature coefficient sensor. As the temperature of the sensor increases, so does the resistance. Under normal operating conditions, the resistance of the thermistor is low which will result in a low input signal. As the increasing temperature causes the resistance of the thermistor to increase, the sensor will trigger an over temperature fault.

The thermistor is connected between Pin 2 and Signal Common. The nominal trip value of the sensor is 1.385 k $\Omega$ . The circuit includes a 12 k $\Omega$  internal pull-up resistor which corresponds to a trip voltage of +0.52 V.

**Table 2-18: Thermistor Input Pin on the Feedback Connector**

| Pin # | Description                       | In/Out/Bi |
|-------|-----------------------------------|-----------|
| 2     | Motor Over Temperature Thermistor | Input     |

**Figure 2-20: Thermistor Input Schematic (Feedback Connector)**




**2.3.4. Encoder Fault Input**

The encoder fault input is for use with encoders that have a fault output. This is provided by some manufacturers and indicates a loss of encoder function. The active state of this input is parameter configurable and the controller should be configured to disable the axis when the fault level is active. The nominal trip voltage of the encoder fault input is +2.5 V.

**Table 2-19: Encoder Fault Input Pin on the Feedback Connector**

| Pin # | Description         | In/Out/Bi |
|-------|---------------------|-----------|
| 23    | Encoder Fault Input | Input     |

**Figure 2-21: Encoder Fault Input Schematic (Feedback Connector)**



### 2.3.5. End of Travel and Home Limit Inputs

End of Travel (EOT) limits are required to define the end of the physical travel on linear axes. Positive or clockwise motion is stopped by the clockwise (CW) end of travel limit input. Negative or counterclockwise motion is stopped by the counterclockwise (CCW) end of travel limit input. The Home Limit switch can be parameter configured for use during the home cycle, however, the CW or CCW EOT limit is typically used instead. All of the end-of-travel limit inputs accept 0-24 VDC level signals. Limit directions are relative to the encoder polarity in the diagnostics display (refer to [Figure 2-24](#)).

**Table 2-20: End of Travel and Home Limit Pins on the Feedback Connector**

| Pin # | Description                          | In/Out/Bi |
|-------|--------------------------------------|-----------|
| 12    | Clockwise End of Travel Limit        | Input     |
| 16    | +5V Power                            | Output    |
| 20    | Signal Common                        | Output    |
| 21    | Signal Common                        | Output    |
| 22    | Home Switch Input                    | Input     |
| 24    | Counterclockwise End of Travel Limit | Input     |

The active state (High/Low) of the EOT limits is software selectable (by the EndOfTravelLimitSetup axis parameter). [Figure 2-22](#) shows the possible wiring configurations for normally-open and normally-closed switches and the parameter setting to use for each configuration.



**IMPORTANT:** Use NPN-type normally-closed limit switches (Active High) to provide fail-safe behavior in the event of an open circuit.

Figure 2-22: End of Travel and Home Limit Input Connections






Figure 2-23: End of Travel and Home Limit Input Schematic (Feedback Connector)



**2.3.5.1. End of Travel and Home Limit Phasing**

If the EOT limits are reversed, you will be able to move further into a limit but be unable to move out. To correct this, swap the connections to the CW and CCW inputs at the Feedback connector or swap the CW and CCW limit functionality in the software using the EndOfTravelLimitSetup parameter. View the logic level of the EOT limit inputs in the Diagnostics display (shown in [Figure 2-24](#)).

**Figure 2-24: End of Travel and Home Limit Input Diagnostic Display**



### 2.3.6. Brake Outputs

The drive has a dedicated brake control circuit. Configure the brake with the BrakeSetup parameter for automatic control (typical). You can also use software commands to directly control the brake output.

**Table 2-21: Brake Output Pins on the Feedback Connector**


| Pin # | Description    | In/Out/Bi |
|-------|----------------|-----------|
| 13    | Brake Output - | Output    |
| 25    | Brake Output + | Output    |

**Table 2-22: Brake Control Specifications**

| Specification   | Value  |
|-----------------|--------|
| Maximum Voltage | 24 VDC |
| Maximum Current | 1 A    |

A varistor must be connected across the brake to minimize voltage transients.

**Figure 2-25: Brake Connected to the 25-Pin Feedback Connector (Typical)**



## 2.4. Safe Torque Off Input (STO)

The STO circuit is comprised of two identical channels, each of which must be energized in order for the drive to produce motion. Each STO input is opto-isolated and accepts 24 V levels directly without the need for external current limiting resistors.



**IMPORTANT:** The drive might be equipped with an STO bypass circuit board. The bypass circuit board defeats the STO safety circuit and allows the system to run at all times. To use the STO safety functionality, remove the circuit board and make connections as outlined in this section.



**IMPORTANT:** The application circuit and its suitability for the desired safety level is the sole responsibility of the user of the drive.



**WARNING:** STO wires must be insulated to prevent short circuits between connector pins. The primary concern is a short circuit between STO 1 IN and STO 2 IN wire strands.

**Table 2-23: STO Connector Pinout**

| Pin # | Signal         | Description  | In/Out/Bi | Connector |
|-------|----------------|--|-----------|-----------|
| 1     | Power Supply + | Use only to defeat STO by connecting to STO 1 IN and STO 2 IN. Not for customer use. | Output    |           |
| 2     | STO 1 IN       | STO Channel 1 Positive Input   | Input     |           |
| 3     | RETURN         | STO Negative Input   | Input     |           |
| 4     | STO 2 IN       | STO Channel 2 Positive Input   | Input     |           |
| 5     | Power Supply - | Use only to defeat STO by connecting to RETURN. Not for customer use.                | Output    |           |

**Table 2-24: Mating Connector Part Numbers for the STO Connector**

| Description          | Aerotech P/N | Phoenix P/N | Tightening Torque (Nm) | Wire Size: AWG [mm <sup>2</sup> ] |
|----------------------|--------------|-------------|------------------------|-----------------------------------|
| 5-Pin Terminal Block | ECK02393     | 1827622     | 0.22 - 0.25            | 2.5 - 0.05 [14-30]                |

**Table 2-25: STO Electrical Specifications**


| Status                                 | Value                                   |
|--|---|
| STO off (motion allowed)               | 18-24 V, 7 ma                           |
| STO on (safe state entered, no motion) | 0-6 V                                   |
| Recommended Wire Gauge                 | 22-26 AWG (0.5 - 0.14 mm <sup>2</sup> ) |
| STO System Power Supply                | PELV                                    |
| STO Wire Length (maximum)              | 50 m                                    |

Figure 2-26 shows one safety device connected to multiple drives in parallel.



**WARNING:** The drive does not check for short circuits on the external STO wiring. If this is not done by the external safety device, short circuits on the wiring must be excluded. Refer to EN ISO 13849-2. For Category 4 systems, the exclusion of short circuits is mandatory.

**Figure 2-26: Typical STO Configuration**





### 2.4.1. STO Standards

Table 2-26 describes and specifies the safety requirements at the system level for the Safe Torque Off (STO) feature of the drive. This assumes that diagnostic testing is performed according to Section 2.4.4. and Table 2-27.

**Table 2-26: STO Standards**

| Standard                          | Maximum Achievable Safety |
|-----------------------------------|---------------------------|
| EN/IEC 61800-5- 2:2016            | SIL 3                     |
| EN/IEC 61508-1:2010               | SIL 3                     |
| EN/IEC 61508-2:2010               | SIL 3                     |
| EN ISO 13849-1:2015               | Category 4, PL e          |
| EN/IEC 62061:2005 with Amendments | SIL 3                     |

**Table 2-27: STO Standards Data**

| Standard                            | Value  |
|-------------------------------------|--|
| EN ISO 13849-1:2015                 | MTTF <sub>D</sub> > 1000 years,<br>DC <sub>AVG</sub> 99%<br>Maximum PL e, Category 4   |
| EN ISO 13849-1:2015<br>EN/IEC 61508 | Lifetime = 20 years<br>No proof test required<br>Interval for manual STO test: <ul style="list-style-type: none"> <li>• Once per year for SIL2/PL d/category 3</li> <li>• Once per three months for SIL3/PL e/category 3</li> <li>• Once per day for SIL3/PL e/category 4</li> </ul> |
| EN/IEC 61508                        | SIL3<br>PFH < 3 FIT<br>SFF > 99%   |

### 2.4.2. STO Functional Description

The motor can only be activated when voltage is applied to both STO 1 and STO 2 inputs. The STO state will be entered if power is removed from either the STO 1 or the STO 2 inputs. When the STO state is entered, the motor cannot generate torque or force and is therefore considered safe.

The STO function is implemented with two redundant channels in order to meet stated performance and SIL levels. STO 1 disconnects the high side power amplifier transistors and STO 2 disconnects the low side power amplifier transistors. Disconnecting either set of transistors effectively prevents the drive from being able to produce motion.

The drive software monitors each STO channel and will generate an Emergency Stop software fault when either channel signals the stop state. Each STO channel contains a fixed delay which allows the drive to perform a controlled stop before the power amplifier transistors are turned off.

A typical configuration requiring a controlled stop has the Emergency Stop Fault mask bit set in the FaultMask, FaultMaskDecel, and FaultMaskDisable parameters. This stops the axis using the rate specified by the AbortDecelRate parameter. The software will disable the axis as soon as the deceleration ramp is complete. This is typically configured to occur before the STO channel turns off the power amplifier transistors.

The software controlled stop functionality must be excluded when considering overall system safety. This is because the software is not safety rated and cannot be included as part of the safety function.

The drive will tolerate short diagnostic pulses on the STO 1+ and STO 2+ inputs. The parameter "STOPulseFilter" specifies the maximum pulse width that the drive will ignore.

To resume normal operation, apply power to both STO 1 and STO 2 inputs and use the *Acknowledge All* button or the AcknowledgeAll() or FaultAcknowledge() function to clear the Emergency Stop software fault. The recommended use of the Emergency Stop Fault fault mask bits prevent the system from automatically restarting.

You can achieve longer delay times through the use of an external delay timer, such as the Omron G9SA-321 Safety Relay Unit. Place this device between the system ESTOP wiring and the drive's STO inputs. Connect the ESTOP signal directly to a digital input, in addition to the external timer, to allow the drive to begin a software-controlled stop as soon as the ESTOP signal becomes active. Use the EmergencyStopFaultInput parameter to configure a digital input as an ESTOP input.

Non-standard STO delay times are provided by special factory order. In this case, the non-standard STO delay time is indicated by a label placed on the slice amplifier's main connector (STO DELAY = xx sec).

**Table 2-28: STO Signal Delay**

|                | Value        |
|----------------|--------------|
| STO Time Delay | 450-550 msec |

**Table 2-29: Motor Function Relative to STO Input State**

| STO 1                    | STO 2                    | Motor Function   |
|--------------------------|--------------------------|------------------|
| Unpowered                | Unpowered                | No force/torque  |
| Unpowered <sup>(1)</sup> | Powered <sup>(1)</sup>   | No force/torque  |
| Powered <sup>(1)</sup>   | Unpowered <sup>(1)</sup> | No force/torque  |
| Powered                  | Powered                  | Normal Operation |

1. This is considered a Fault Condition since STO 1 and STO 2 do not match. Refer to [Section 2.4.4](#).

### 2.4.3. STO Startup Validation Testing

Verify the state of the STO 1 and STO 2 channels by manually activating the external STO hardware. Each STO channel must be tested separately in order to detect potential short circuits between the channels. The current state of the STO 1 and STO 2 inputs is shown in the Status Utility. A “-” indicates that the STO input is powered by a high voltage level (24 V). An “ON” indicates that the voltage source has been removed from the input (open circuit or 0 V), and that the STO channel is in the safe state.



**DANGER:** The STO circuit does not remove lethal voltage from the motor terminals. AC mains power must be removed before servicing.

### 2.4.4. STO Diagnostics


Activation of STO means removing power from the drive's STO inputs. This is typically done by pressing the emergency stop switch. The drive initiates a diagnostic check every time the STO is activated after the Diagnostic Test Delay Time has elapsed. The diagnostic check verifies that each channel has entered the safe state. The drive is held in the safe state if it determines that one of the channels has not properly entered the safe state. An open circuit or short to 24 V in either STO channel will result in this condition (refer to [Section 2.4.3.](#)). The Status Utility screen can be used to verify the levels of the STO input signals while trouble shooting.

In order to meet the listed SIL level, the STO circuit must be activated (power removed from both inputs) according to the interval specified in [Table 2-27.](#)

**Table 2-30: STO Timing**

| Time | Description  | Value        |
|------|--|--------------|
| T1   | STO Delay Time (STO input active to motor power off)   | 450-550 msec |
| T2   | STO deactivated to motor power on (the software is typically configured so that the motor does not automatically re-energize). | < 1 msec     |
| T3   | Diagnostic Test Delay Time   | 550-610 msec |

**Figure 2-27: STO Timing**



The software is typically configured to execute a controlled stop when the STO state is first detected. If power is reapplied to the STO inputs before the STO Delay Time, an STO hardware shutdown will not occur but a software stop may, depending on the width of the STO pulse. The controller will ignore STO active pulses shorter in length than the STOPulseFilter parameter setting.

## 2.5. HyperWire Interface

The HyperWire bus is the high-speed communications connection from the controller. It operates at 2 gigabits per second. The controller sends all command and configuration information through the HyperWire bus.

HyperWire cables can be safely connected to or disconnected from a HyperWire port while the PC and/or drive is powered on. However, any changes to the HyperWire network topology will disrupt communication and you must reset the controller to re-establish communication.



**WARNING:** Do not connect or disconnect HyperWire cables while you are loading firmware or damage to the drives may occur.

**Table 2-31: HyperWire Card Part Number**

| Part Number    | Description                          |
|----------------|--------------------------------------|
| HYPERWIRE-PCIE | HyperWire adapter, PCIe x4 interface |

**Table 2-32: HyperWire Cable Part Numbers**

| Part Number        | Description                             |
|--------------------|---|
| HYPERWIRE-AO10-5   | HyperWire cable, active optical, 0.5 m  |
| HYPERWIRE-AO10-10  | HyperWire cable, active optical, 1.0 m  |
| HYPERWIRE-AO10-30  | HyperWire cable, active optical, 3.0 m  |
| HYPERWIRE-AO10-50  | HyperWire cable, active optical, 5.0 m  |
| HYPERWIRE-AO10-200 | HyperWire cable, active optical, 20.0 m |

## 2.6. Sync Port

The Sync port is a bi-directional high speed proprietary interface that lets you transmit encoder signals between drives. This is typically used for multi-axis PSO applications where one or two drives send their encoder signals to a main drive that has the PSO logic and PSO output signal. The drive contains two Sync ports, labeled A and B.

To avoid signal contention, all Sync ports default to the input state during reset and immediately after power is applied to the drive.

**Table 2-33: Sync-Related Functions**

| Function   | Description                                       |
|--|---|
| DriveEncoderOutputConfigureDivider(),<br>DriveEncoderOutputConfigureInput(),<br>DriveEncoderOutputOn(),<br>DriveEncoderOutputOff() | Configure each Sync port as an input or an output |
| PsoDistanceConfigureInputs()   | Let the PSO to track the SYNC A or SYNC B port.   |
| PsoWindowConfigureInput()  |   |

The Sync port uses low-voltage differential signaling (LVDS) and standard USB 3.0 type A (cross over) cables.

**Table 2-34: Sync Port Cables**

| Part Number | Description  |
|-------------|--|
| CBL-SYNC-3  | Length 3 dm; Connectors: USB Type A to USB Type A  |
| CBL-SYNC-5  | Length 5 dm; Connectors: USB Type A to USB Type A  |
| CBL-SYNC-7  | Length 7 dm; Connectors: USB Type A to USB Type A  |
| CBL-SYNC-10 | Length 10 dm; Connectors: USB Type A to USB Type A |

## 2.7. System Interconnection

Figure 2-28: System Wiring Drawing (Best Practice)





Figure 2-29: System Interconnection Drawing (Best Practice)



|  |  |  |
|--|--|--|
| <p><b>! ! ATTENTION ! !</b></p> <p>The system integrator or end user is responsible for all safety compliance and technical requirements for the system drives, wiring, and power supply sizing.</p> <p><b>IMPORTANT:</b> Read all parts of this manual before you install or operate the XL2e or before you do maintenance to your system.</p> <ul style="list-style-type: none"> <li>- To prevent injury to you and damage to the equipment, obey the precautions in this manual.</li> <li>- If you do not understand the information in this manual, contact Aerotech Global Technical Support.</li> </ul> <p>For EMC compliance, mount all system components on to a common <b>conductive</b> metal panel.</p> <ul style="list-style-type: none"> <li>Do not use a panel that has a painted or non-conductive coat applied.</li> <li>You can use a panel with a conductive surface coat.</li> </ul> <p><b>SYSTEM WIRING / ROUTING</b></p> <ul style="list-style-type: none"> <li>Separate VAC and VDC wiring.</li> <li>Separate Motor Supply wiring from Control Supply, Low-Voltage I/O, and Feedback signal wiring.</li> <li>Separate the motor cable and its termination wiring from the Control Supply, Low-Voltage I/O, Feedback signal wiring, and VAC/VDC supply wiring.</li> </ul> | <p><b>SYSTEM WIRING SPECIFICATIONS</b></p> <ul style="list-style-type: none"> <li>Use twisted pair conductors with wire lengths as short as possible.</li> <li>AC POWER Wire Size: 1.3 mm<sup>2</sup> (18 AWG)</li> <li>MOTOR POWER Wire Size: 0.5 mm<sup>2</sup> (20 AWG)</li> <li>CONTROL SUPPLY Wire Size: 0.34 mm<sup>2</sup> (22 AWG)</li> <li>WIRE CONFORMITY: North America (UL AWG) / European Union (IHMW-CE).</li> </ul> <p><b>SYSTEM CONTROL and MOTOR VDC POWER SUPPLIES</b></p> <p><b>Minimum Requirements:</b></p> <ul style="list-style-type: none"> <li>Double Insulated</li> <li>Short-Circuit and Over-Voltage protection</li> <li>Approvals: UL, CE</li> </ul> <p><b>Recommended Power Supplies:</b></p> <ul style="list-style-type: none"> <li>24 VDC Control Supply: Mean Well P/N: NDR-75-24 (DIN Rail Power Supplies: 75 W 24 V 3.2 A)</li> <li>148 VDC Bipolar Motor Supply Pair: Mean Well P/N: NDR-480-48 (DIN Rail Power Supplies: 480 W 48 V 10 A)</li> <li>124 VDC Bipolar Motor Supply Pair: Mean Well P/N: NDR-240-24 (DIN Rail Power Supplies: 240 W 24 V 10 A)</li> </ul> <p>"Refer to the Mean Well 'NDR Series Installation Manual'." The system designer must determine power supply requirements.</p> <p><b>XL2e DRIVES</b></p> <ul style="list-style-type: none"> <li>Refer to assemblies (A1), (A2), and (A3)</li> <li>Refer to the XL2e Hardware Manual</li> <li>If the drive(s) were purchased as an integrated system, refer to the "System Interconnections" drawing included with the system documentation.</li> </ul> | <p><b>SYSTEM PROTECTIVE EARTH (PE) GROUNDS</b></p> <ul style="list-style-type: none"> <li>Keep PE wires as short as possible.</li> <li>Terminate each PE directly to the grounded component panel (refer to Note 1).</li> </ul> <p><b>AXIS FEEDBACK CABLE FERRITE EMC FILTERS</b></p> <ul style="list-style-type: none"> <li>Use P/N: Fair-Rite #344616781 (Aerotech # EC202348) clamp-on filter.</li> <li>Apply an clamp as close as possible to the FEEDBACK connector backshell as illustrated.</li> </ul> <p><b>AXIS MOTOR CABLE FERRITE EMC FILTERS</b></p> <ul style="list-style-type: none"> <li>Slide Fair-Rite Core P/N: Z631626402 (Aerotech P/N: EC202367) over motor-phase leads A, B, and C.</li> <li>Locate as close as possible to the drive motor output terminals.</li> <li>NOTE: Aerotech motor cables are factory-built to incorporate an EMC filter in the cable.</li> </ul> <p><b>SYSTEM AC POWER EMC FILTER Part Number (Recommended)</b></p> <p>Schaffner P/N: FN2070-10-06 (Aerotech P/N: EC200264) or equivalent.</p> <p><b>SURGE PROTECTION DEVICES (RECOMMENDED)</b></p> <ul style="list-style-type: none"> <li>Class I, ~100 VLN Supply: Littelfuse SPD2-150-1P1-R</li> <li>Class II, ~240 VLN Supply: Littelfuse SPD2-300-1P1-R</li> <li>Class III, ~240 VLN Supply: Littelfuse SPD2-300-2P0-R</li> </ul> <p><b>SYSTEM AC POWER</b></p> <ul style="list-style-type: none"> <li>Fuses or Circuit Breaker protection is required.</li> <li>Voltages and Currents are dependent on the selected power supplies and system axis requirements (refer to Note 4).</li> </ul> <p><b>DIN RAIL Part Number (Recommended)</b></p> <p>Use Phoenix NS 35 7.5 PERP 2000M - 0801733 or equivalent.</p> <p>The information on this page is for reference only and represents best practice applications.</p> |
|--|--|--|



## **2.8. PC Configuration and Operation Information**


For more information about hardware requirements, PC configuration, programming, system operation, and utilities, refer to the [Help file](#).

*This page intentionally left blank.*

## Chapter 3: -EB1 I/O Option Board

The -EB1 I/O option board has 8 digital inputs, 8 digital outputs, 1 analog input, 1 analog output, and PSO outputs.

**Figure 3-1: XL2e with -EB1 I/O Option Board Connectors**




### 3.1. PSO Interface [-EB1]

The Position Synchronized Output (PSO) signal is available on the -EB1 option board in two signal formats: TTL and Isolated.

**Table 3-1: PSO Specifications [-EB1]**

| Specification                                   |          | Value            |
|---|----------|------------------|
| Output  | TTL      | 5 V, 50 mA (max) |
|   | Isolated | 5-24 V, 250 mA   |
| Maximum PSO Output (Fire) Frequency             | TTL      | 12.5 MHz         |
|   | Isolated | 5 MHz            |
| Output Latency<br>[Fire event to output change] | TTL      | 5 ns             |
|   | Isolated | 150 ns           |

**Table 3-2: PSO Interface Connector Pinout [-EB1]**

| Pin # | Description      | In/Out/Bi | Connector   |
|-------|------------------|-----------|---|
| 1     | PSO Output+      | Output    |  |
| 2     | PSO Output-      | Output    |   |
| 3     | PSO Output (TTL) | Output    |   |
| 4     | Ground           | N/A       |   |


**Table 3-3: Mating Connector Part Numbers for the PSO Interface Connector [-EB1]**

| Type                 | Aerotech P/N | Third Party P/N | Wire Size: mm <sup>2</sup> [AWG] |
|----------------------|--------------|-----------------|----------------------------------|
| 4-Pin Terminal Block | ECK02399     | Phoenix 1768004 | 0.5- 0.14 [20-26]                |


**Isolated Signals**

This output signal is a fully-isolated 5-24V compatible output capable of sourcing or sinking current. This output is normally open and only conducts current when a PSO fire event occurs. The PSO Isolated Outputs are overload protected and will turn off if the maximum output current is exceeded.

**Figure 3-2: PSO Output Sources Current**




**Figure 3-3: PSO Output Sinks Current**



**TTL Signals**

This output signal is a 5V TTL signal which is used to drive an opto coupler or general purpose TTL input. This signal is active high and is driven to 5V when a PSO fire event occurs.

**Figure 3-4: PSO TTL Outputs Schematic**



### 3.2. Auxiliary Encoder Input [-EB1]

The Auxiliary Encoder connector gives you a second encoder input channel. This channel is typically used for dual loop applications.

Use the `AuxiliaryFeedbackType` parameter to configure the drive to accept an encoder signal type.


Square Wave encoder signals: [Section 3.2.1](#).

Absolute encoder signals: [Section 3.2.2](#).

Sine Wave encoder signals (with the -MX3 option): [Section 3.2.3](#).

You can configure the Auxiliary Encoder interface as an output that will transmit encoder signals for external use. Use the `DriveEncoderOutputConfigureInput()` function to configure the Sine  $\pm$  and Cosine  $\pm$  connector pins as RS-422 outputs. You can only echo incremental square wave primary encoder inputs or, with the with the -MX2 or -MX3 option, incremental sine wave primary encoder inputs.

**Table 3-4: Auxiliary Encoder Connector Pinout**

| Pin# | Description              | In/Out/Bi     | Connector  |
|------|--------------------------|---------------|--|
| 1    | Auxiliary Marker -       | Input         |  |
| 2    | Auxiliary Cosine+        | Bidirectional |  |
|      | Absolute Encoder Clock + | Output        |  |
| 3    | Auxiliary Cosine-        | Bidirectional |  |
|      | Absolute Encoder Clock - | Output        |  |
| 4    | Auxiliary Sine+          | Bidirectional |  |
|      | Absolute Encoder Data +  | Bidirectional |  |
| 5    | Encoder Cable Shield     | N/A           |  |
| 6    | Auxiliary Marker +       | Input         |  |
| 7    | +5 Volt (500 mA max)     | Output        |  |
| 8    | Signal Common            | Output        |  |
| 9    | Auxiliary Sine-          | Bidirectional |  |
|      | Absolute Encoder Data -  | Bidirectional |  |

**Table 3-5: Mating Connector Part Numbers for the AUX Connector**

| Adapter Cable  | Aerotech P/N | Third Party P/N  |
|--|--------------|------------------|
| 9-Pin Standard D-style                                     | C20931       | N/A              |
| 25-Pin Standard D-style                                    | C20932       | N/A              |
| Flying Leads   | ECZ01343     | Molex 83421-9042 |
| 9-Pin Micro D-Style (for a second Auxiliary Encoder Input) | ECZ03125     | N/A              |


### 3.2.1. Square Wave Encoder (Auxiliary)

The drive accepts RS-422 square wave encoder signals. The drive will generate a feedback fault if it detects an invalid signal state caused by an open or shorted signal connection. Use twisted-pair wiring for the highest performance and noise immunity.

**Table 3-6: Square Wave Encoder Specifications**

| Specification          | Value  |
|------------------------|--|
| Encoder Frequency      | 10 MHz maximum (25 ns minimum edge separation) |
| x4 Quadrature Decoding | 40 million counts/sec                          |

**Figure 3-5: Square Wave Encoder Interface (Aux Connector)**




### 3.2.2. Absolute Encoder (Auxiliary)

The drive retrieves absolute position data along with encoder fault information through a serial data stream from the absolute encoder. Use twisted-pair wiring for the highest performance and noise immunity. You cannot use an absolute encoder with incremental signals on the Auxiliary Encoder Connector.

Refer to [Figure 3-6](#) for the serial data stream interface.

Refer to the [Help file](#) for information on how to set up your EnDat or BiSS absolute encoder parameters.

**Figure 3-6: Absolute Encoder Schematic (Auxiliary Encoder Connector)**





### 3.2.3. Sine Wave Encoder (Auxiliary) [-MX3 Option]

The Sine Wave Encoder option provides higher positioning resolution by subdividing the fundamental output period of the encoder into smaller increments. The amount of subdivision is specified by the AuxiliaryEncoderMultiplicationFactor parameter. Use Encoder Tuning to adjust the value of the gain, offset, and phase balance controller parameters to get the best performance. For more information, refer to the [Help file](#).

You cannot use the sine wave encoder on the auxiliary connector with the -MX3 multiplier option as an input to the PSO. The -MX3 option does not generate emulated quadrature signals from the auxiliary connector.


For the highest performance, use twisted pair double-shielded cable with the inner shield connected to signal common and the outer shield connected to frame ground. Do not join the inner and outer shields in the cable.


**Table 3-7: Sine Wave Encoder Specifications**

| Specification   | Value  |           |
|---|--|-----------|
|   | Primary                                      | Auxiliary |
| Input Frequency (max)                                   | 200 kHz, 2 MHz                               | 200 kHz   |
| Input Amplitude <sup>(1)</sup>                          | 0.6 to 1.75 Vpk-pk                           |           |
| Interpolation Factor (max)                              | -MX2   | 65,536    |
|   | -MX3   | 65,536    |
| -MX2/-MX3 Primary Encoder Channel Interpolation Latency | 800 nsec (analog input to quadrature output) |           |
| Input Common Mode                                       | 1.5 to 3.5 VDC                               |           |

(1) Measured as SIN(+) - SIN(-) or COS(+) - COS(-)

**Figure 3-7: Sine Wave Encoder Phasing Reference Diagram**




**Figure 3-8: Sine Wave Encoder Schematic (Aux Connector)**

### 3.3. Analog I/O [-EB1]

The Analog I/O connector has one differential analog input and one analog output.

**Table 3-8: Analog I/O Connector Pinout [-EB1]**

| Pin# | Description       | In/Out/Bi | Connector   |
|------|-------------------|-----------|---|
| 1    | +5 V (250 mA max) | Output    |  |
| 2    | Analog Input 0+   | Input     |   |
| 3    | Analog Input 0-   | Input     |   |
| 4    | Ground            | N/A       |   |
| 5    | Ground            | N/A       |   |
| 6    | Analog Output 0   | Output    |   |

**Table 3-9: Mating Connector Part Numbers for the Analog I/O Connector [-EB1]**

| Type                 | Aerotech P/N | Third Party P/N | Wire Size: mm <sup>2</sup> [AWG] |
|----------------------|--------------|-----------------|----------------------------------|
| 6-Pin Terminal Block | ECK02405     | Phoenix 1704755 | 0.5 - 0.14 [20-26]               |

### 3.3.1. Analog Output 0 [-EB1]

The analog output can be set from within a program or it can be configured to echo the state of select servo loop nodes.

The analog output is set to zero when you power on the system or reset the drive.


**Table 3-10: Analog Output Specifications [-EB1]**

| Specification     | Value          |
|-------------------|----------------|
| Output Voltage    | -10 V to +10 V |
| Output Current    | 5 mA           |
| Resolution (bits) | 16 bits        |

**Table 3-11: Analog Output Pins on the Analog I/O Connector [-EB1]**

| Pin# | Description     | In/Out/Bi |
|------|-----------------|-----------|
| 5    | Ground          | N/A       |
| 6    | Analog Output 0 | Output    |

**Figure 3-9: Analog Output Schematic [-EB1]**



### 3.3.2. Analog Input (Differential) [-EB1]

To interface to a single-ended, non-differential voltage source, connect the signal common of the source to the negative input and connect the analog source signal to the positive input. A floating signal source must be referenced to the analog common. Refer to Figure 3-10.


**Table 3-12: Differential Analog Input Specifications [-EB1]**

| Specification   | Value                         |
|---|-------------------------------|
| (AI+) - (AI-)   | +10 V to -10 V <sup>(1)</sup> |
| Resolution (bits)                                     | 16 bits                       |
| Input Impedance                                       | 1 MΩ                          |
| 1. Signals outside of this range may damage the input |                               |

**Table 3-13: Analog Input Pins on the Analog I/O Connector [-EB1]**

| Pin# | Description       | In/Out/Bi |
|------|-------------------|-----------|
| 1    | +5 V (250 mA max) | Output    |
| 2    | Analog Input 0+   | Input     |
| 3    | Analog Input 0-   | Input     |
| 4    | Ground            | N/A       |

**Figure 3-10: Analog Input Schematic [-EB1]**



### 3.4. Digital Outputs [-EB1]

Optically-isolated solid-state relays drive the digital outputs. You can connect the digital outputs in current sourcing or current sinking mode but you must connect all four outputs in a port in the same configuration. Refer to [Figure 3-12](#) and [Figure 3-13](#).

The digital outputs are not designed for high-voltage isolation applications and they should only be used with ground-referenced circuits.


You must install suppression diodes on digital outputs that drive relays or other inductive devices. To see an example of a current sourcing output that has diode suppression, refer to [Figure 3-12](#). To see an example of a current sinking output that has diode suppression, refer to [Figure 3-13](#).

The digital outputs have overload protection. They will resume normal operation when the overload is removed.

**Table 3-14: Digital Output Specifications [-EB1]**

| Digital Output Specifications | Value                             |
|-------------------------------|-----------------------------------|
| Maximum Voltage               | 24 V (26 V Maximum)               |
| Maximum Sink/Source Current   | 250 mA/output                     |
| Output Saturation Voltage     | 0.9 V at maximum current          |
| Output Resistance             | 3.7 $\Omega$                      |
| Rise / Fall Time              | 250 $\mu$ s (2K pull up to 24V)   |
| Reset State                   | Output Off (High Impedance State) |


**Table 3-15: Digital Output Connector Pinout [-EB1]**

| Pin# | Description                   | In/Out/Bi | Connector  |
|------|-------------------------------|-----------|--|
| 1    | Output Common for Outputs 0-3 | Output    |  |
| 2    | Output 0 (Optically-Isolated) | Output    |  |
| 3    | Output 1 (Optically-Isolated) | Output    |  |
| 4    | Output 2 (Optically-Isolated) | Output    |  |
| 5    | Output 3 (Optically-Isolated) | Output    |  |
| 6    | Output Common for Outputs 4-7 | Output    |  |
| 7    | Output 4 (Optically-Isolated) | Output    |  |
| 8    | Output 5 (Optically-Isolated) | Output    |  |
| 9    | Output 6 (Optically-Isolated) | Output    |  |
| 10   | Output 7 (Optically-Isolated) | Output    |  |

**Table 3-16: Mating Connector Part Numbers for the Digital Output Connector [-EB1]**


| Mating Connector      | Aerotech P/N | Third Party P/N | Wire Size: mm <sup>2</sup> [AWG] |
|-----------------------|--------------|-----------------|----------------------------------|
| 10-Pin Terminal Block | ECK02395     | Phoenix 1700841 | 0.5 - 0.14 [20-26]               |

**Figure 3-11: Digital Outputs Schematic [-EB1]**



**Figure 3-12: Digital Outputs Connected in Current Sourcing Mode [-EB1]**


Digital Output Connector [-EB1]



 DIODE REQUIRED ON EACH OUTPUT THAT DRIVES AN INDUCTIVE DEVICE (COIL), SUCH AS A RELAY.

**Figure 3-13: Digital Outputs Connected in Current Sinking Mode [-EB1]**

Digital Output Connector [-EB1]



 DIODE REQUIRED ON EACH OUTPUT THAT DRIVES AN INDUCTIVE DEVICE (COIL), SUCH AS A RELAY.



### 3.5. Digital Inputs [-EB1]

Input bits are arranged in groups of 4 and each group shares a common pin. This lets a group be connected to current sourcing or current sinking devices, based on the connection of the common pin in that group.

To be able to connect an input group to current sourcing devices, connect the input group's common pin to the power supply return (-). Refer to [Figure 3-15](#).


To be able to connect an input group to current sinking devices, connect the input group's common pin to the power supply source (+). Refer to [Figure 3-16](#).

The digital inputs are not designed for high-voltage isolation applications. They should only be used with ground-referenced circuits.

**Table 3-17: Digital Input Specifications [-EB1]**

| Input Voltage | Approximate Input Current | Turn On Time | Turn Off Time |
|---------------|---------------------------|--------------|---------------|
| +5 V to +24 V | 6 mA                      | 10 $\mu$ s   | 43 $\mu$ s    |


**Table 3-18: Digital Input Connector Pinout [-EB1]**

| Pin# | Description                  | In/Out/Bi | Connector  |
|------|------------------------------|-----------|--|
| 1    | Input Common for Inputs 0-4  | Output    |  |
| 2    | Input 0 (Optically-Isolated) | Input     |  |
| 3    | Input 1 (Optically-Isolated) | Input     |  |
| 4    | Input 2 (Optically-Isolated) | Input     |  |
| 5    | Input 3 (Optically-Isolated) | Input     |  |
| 6    | Input Common for Inputs 4-7  | Output    |  |
| 7    | Input 4 (Optically-Isolated) | Input     |  |
| 8    | Input 5 (Optically-Isolated) | Input     |  |
| 9    | Input 6 (Optically-Isolated) | Input     |  |
| 10   | Input 7 (Optically-Isolated) | Input     |  |

**Table 3-19: Mating Connector Part Numbers for the Digital Input Connector [-EB1]**


| Mating Connector      | Aerotech P/N | Third Party P/N | Wire Size: mm <sup>2</sup> [AWG] |
|-----------------------|--------------|-----------------|----------------------------------|
| 10-Pin Terminal Block | ECK02395     | Phoenix 1700841 | 0.5 - 0.14 [20-26]               |

**Figure 3-14: Digital Inputs Schematic [-EB1]**




Each bank of four inputs must be connected in an all sourcing or all sinking configuration.

**Figure 3-15: Digital Inputs Connected to Current Sourcing (PNP) Devices [-EB1]**



**Figure 3-16: Digital Inputs Connected to Current Sinking (NPN) Devices [-EB1]**



## Chapter 4: Cables and Accessories



**IMPORTANT:** Find Aerotech cable drawings on the website at <http://www.aerotechmotioncontrol.com/manuals/index.aspx>.

**Table 4-1: Standard Interconnection Cables**

| Cable Part #              | Description   |
|---------------------------|---|
| Joystick                  | Refer to <a href="#">Section 4.2. Joystick Interface</a>  |
| Handwheel                 | Refer to <a href="#">Section 4.3. Handwheel Interface</a> |
| C20934-XX or<br>C20935-XX | BB-MP Interconnect Cable (Refer to the BB-MP manual)      |

### 4.1. DIN Rail Mounting

**DIN Rail Mounting Procedure:**

1. Mount the DIN rail clip to the drive. The clip and #6-32 x 1/4 flat head screws are included in the HyperWire-DIN clip kit.
2. Cut the DIN rail so that one complete mounting hole extends beyond the last component at each end.
3. Secure the DIN Rail to the mounting surface with #10-32 screws spaced every six inches.  
NOTE: Do not install the DIN rail to the mounting surface with the components already attached.
4. Install all components on to the DIN rail.




**IMPORTANT:** Refer to the Automation1 PS2 DIN Rail Power Supply hardware manual for more information.

**Table 4-2: Mounting Parts**

|                   | Aerotech P/N  |
|-------------------|---------------|
| DIN Rail          | EAM00914      |
| DIN Rail Clip Kit | HyperWire-DIN |

**Figure 4-1: Din Rail Clip Dimensions**




### 4.2. Joystick Interface

Aerotech Multi-Axis Joystick (NEMA12 (IP54) rated) is powered from 5 V and has a nominal 2.5 V output in the center detent position. Three buttons are used to select axis pairs and speed ranges. Joystick control will not activate unless the joystick is in the center location. Third party devices can be used provided they produce a symmetric output voltage within the range of -10 V to +10 V.

Connecting joystick with an Aerotech cable, all Aerotech cables are labeled to identify the connector and connections. The joystick parameters must be set to match the analog and digital I/O connections. Refer to the [Help file](#) for programming information about how to change joystick parameters.

**Figure 4-2: Two Axis Joystick Interface**



### 4.3. Handwheel Interface


A handwheel can be used to manually control axis position. The handwheel must provide 5V differential quadrature signals to the drive.



**IMPORTANT:** You can find instructions on how to enable the handwheel in the online [Help file](#).

Connect a handwheel to the Aux connector as shown in [Figure 4-3](#).

**Figure 4-3: Handwheel Interconnection to the Aux Connector**



## Chapter 5: Maintenance



**IMPORTANT:** For your own safety and for the safety of the equipment:

- Do not remove the cover of the XL2e.
- Do not attempt to access the internal components.

A fuse that needs to be replaced indicates that there is a more serious problem with the system or setup. Contact Global Technical Support for assistance.



**DANGER:** If you must remove the covers and access any internal components be aware of the risk of electric shock.

1. Disconnect the Mains power connection.
2. Wait at least one (1) minute after removing the power supply before doing maintenance or an inspection. Otherwise, there is the danger of electric shock.
3. All tests must be done by an approved service technician. Voltages inside the controller and at the input and output power connections can kill you.

**Table 5-1: LED Description**

| LED    | Color                  | Description  |
|--------|------------------------|--|
| PWR    | GREEN                  | The light will illuminate and remain illuminated while power is applied.                       |
| EN/FLT | GREEN                  | The axis is Enabled.   |
|        | RED                    | The axis is in a Fault Condition.  |
|        | GREEN/RED (alternates) | The axis is Enabled in a Fault Condition.<br>or<br>The light is configured to blink for setup. |

**Table 5-2: Troubleshooting**

| Symptom          | Possible Cause and Solution   |
|------------------|---|
| No Communication | Make sure the power LED is illuminated (this indicates that power is present).                      |
|                  | Make sure that all communication cables (HyperWire, for example) are fully inserted in their ports. |

## 5.1. Preventative Maintenance

Do an inspection of the XL2e and the external wiring one time each month. It might be necessary to do more frequent inspections based on:

- The operating conditions of the system.
- How you use the system.

**Table 5-3: Preventative Maintenance**

| Check  | Action to be Taken  |
|--|---|
| Examine the chassis for hardware and parts that are damaged or loose.<br>It is not necessary to do an internal inspection unless you think internal damage occurred. | Repair all damaged parts.   |
| Do an inspection of the cooling vents.   | Remove all material that collected in the vents.  |
| Examine the work area to make sure there are no fluids and no electrically conductive materials.   | Do not let fluids and electrically conductive material go into the chassis.   |
| Examine all cables and connections to make sure they are correct.  | Make sure that all connections are correctly attached and not loose.<br>Replace cables that are worn.<br>Replace all broken connectors. |

### Cleaning



**DANGER:** Before you clean the XL2e, disconnect the electrical power from the drive.

Use a clean, dry, soft cloth to clean the XL2e. If necessary, use a cloth that is moist with water or isopropyl alcohol. If you use a moist cloth, make sure that moisture does not go into the drive. Also make sure that it does not go onto the outer connectors and components. Internal contamination from the cleaning solution can cause corrosion and electrical short circuits.

Do not clean the labels with a cleaning solution because it might remove the label information.



## 5.2. Fuse Specifications



**WARNING:** Replace fuses only with the same type and value.

**Table 5-4: Control Board Fuse Specifications**

| Fuse | Description                 | Size     | Aerotech P/N | Third Party P/N          |
|------|-----------------------------|----------|--------------|--------------------------|
| F1   | Control Power at +24V Input | 2 A S.B. | EIF01066     | Littelfuse 0473002.MRT1L |
| F201 | Motor Power at B- Input     | 5 A S.B. | EIF01061     | Littlefuse 39215000440   |
| F202 | Motor Power at B+ Input     | 5 A S.B. | EIF01061     | Littlefuse 39215000440   |

*This page intentionally left blank.*

## Appendix A: Warranty and Field Service

Aerotech, Inc. warrants its products to be free from harmful defects caused by faulty materials or poor workmanship for a minimum period of one year from date of shipment from Aerotech. Aerotech's liability is limited to replacing, repairing or issuing credit, at its option, for any products that are returned by the original purchaser during the warranty period. Aerotech makes no warranty that its products are fit for the use or purpose to which they may be put by the buyer, whether or not such use or purpose has been disclosed to Aerotech in specifications or drawings previously or subsequently provided, or whether or not Aerotech's products are specifically designed and/or manufactured for buyer's use or purpose. Aerotech's liability on any claim for loss or damage arising out of the sale, resale, or use of any of its products shall in no event exceed the selling price of the unit.

THE EXPRESS WARRANTY SET FORTH HEREIN IS IN LIEU OF AND EXCLUDES ALL OTHER WARRANTIES, EXPRESSED OR IMPLIED, BY OPERATION OF LAW OR OTHERWISE. IN NO EVENT SHALL AEROTECH BE LIABLE FOR CONSEQUENTIAL OR SPECIAL DAMAGES.

### Return Products Procedure

Claims for shipment damage (evident or concealed) must be filed with the carrier by the buyer. Aerotech must be notified within thirty (30) days of shipment of incorrect material. No product may be returned, whether in warranty or out of warranty, without first obtaining approval from Aerotech. No credit will be given nor repairs made for products returned without such approval. A "Return Materials Authorization (RMA)" number must accompany any returned product(s). The RMA number may be obtained by calling an Aerotech service center or by submitting the appropriate request available on our website ([www.aerotech.com](http://www.aerotech.com)). Products must be returned, prepaid, to an Aerotech service center (no C.O.D. or Collect Freight accepted). The status of any product returned later than thirty (30) days after the issuance of a return authorization number will be subject to review.

Visit [Global Technical Support Portal](#) for the location of your nearest Aerotech Service center.

### Returned Product Warranty Determination

After Aerotech's examination, warranty or out-of-warranty status will be determined. If upon Aerotech's examination a warranted defect exists, then the product(s) will be repaired at no charge and shipped, prepaid, back to the buyer. If the buyer desires an expedited method of return, the product(s) will be shipped collect. Warranty repairs do not extend the original warranty period.

**Fixed Fee Repairs** - Products having fixed-fee pricing will require a valid purchase order or credit card particulars before any service work can begin.

**All Other Repairs** - After Aerotech's evaluation, the buyer shall be notified of the repair cost. At such time the buyer must issue a valid purchase order to cover the cost of the repair and freight, or authorize the product(s) to be shipped back as is, at the buyer's expense. Failure to obtain a purchase order number or approval within thirty (30) days of notification will result in the product(s) being returned as is, at the buyer's expense.

Repair work is warranted for ninety (90) days from date of shipment. Replacement components are warranted for one year from date of shipment.

### Rush Service

At times, the buyer may desire to expedite a repair. Regardless of warranty or out-of-warranty status, the buyer must issue a valid purchase order to cover the added rush service cost. Rush service is subject to Aerotech's approval.

### On-site Warranty Repair

If an Aerotech product cannot be made functional by telephone assistance or by sending and having the customer install replacement parts, and cannot be returned to the Aerotech service center for repair, and if Aerotech determines the problem could be warranty-related, then the following policy applies:

Aerotech will provide an on-site Field Service Representative in a reasonable amount of time, provided that the customer issues a valid purchase order to Aerotech covering all transportation and subsistence costs. For warranty field repairs, the customer will not be charged for the cost of labor and material. If service is rendered at times other than normal work periods, then special rates apply.

If during the on-site repair it is determined the problem is not warranty related, then the terms and conditions stated in the following "On-Site Non-Warranty Repair" section apply.

### On-site Non-Warranty Repair

If any Aerotech product cannot be made functional by telephone assistance or purchased replacement parts, and cannot be returned to the Aerotech service center for repair, then the following field service policy applies:

Aerotech will provide an on-site Field Service Representative in a reasonable amount of time, provided that the customer issues a valid purchase order to Aerotech covering all transportation and subsistence costs and the prevailing labor cost, including travel time, necessary to complete the repair.

### Service Locations

<http://www.aerotech.com/contact-sales.aspx?mapState=showMap>

#### **USA, CANADA, MEXICO**

Aerotech, Inc.  
Global Headquarters

#### **CHINA**

Aerotech China  
Full-Service Subsidiary

#### **GERMANY**

Aerotech Germany  
Full-Service Subsidiary

#### **TAIWAN**

Aerotech Taiwan  
Full-Service Subsidiary

#### **UNITED KINGDOM**

Aerotech United Kingdom  
Full-Service Subsidiary

## Appendix B: Revision History

| Revision | Description  |
|----------|--|
| 1.02     | Added support for Three Phase Stepper Motors: <a href="#">Section 2.2.4</a> .  |
| 1.01     | The following sections have been updated: <ul style="list-style-type: none"><li>• <a href="#">Section 1.1. Electrical Specifications</a></li><li>• <a href="#">Chapter 4: Cables and Accessories</a></li></ul> |
| 1.00     | New manual   |

*This page intentionally left blank.*

# Index

## -EB1

|  |       |
|--|-------|
| Analog Input                                 | 69    |
| Analog Outputs                               | 68    |
| Auxiliary Encoder Input                      | 62    |
| Digital Inputs                               | 67,73 |
| Digital Outputs                              | 67,70 |
| I/O Option Board                             | 59    |
| Position Synchronized Output (PSO) Interface | 60    |

|      |       |
|------|-------|
| -MX2 | 38    |
| -MX3 | 38,65 |

## 2

|            |   |
|------------|---|
| 2006/42/EC | 9 |
| 2011/65/EU | 9 |
| 2014/30/EU | 9 |
| 2014/35/EU | 9 |

## A

|  |    |
|--|----|
| Absolute Encoder (Aux Encoder)                                   | 64 |
| Absolute Encoder (Feedback Connector)                            | 37 |
| Absolute Encoder Schematic (Aux Encoder Connector)               | 64 |
| Absolute Encoder Schematic (Feedback Connector)                  | 37 |
| Agency Approvals   | 10 |
| Altitude   | 22 |
| Ambient Temperature  | 22 |
| Analog Encoder (Aux Connector)                                   | 65 |
| Analog Encoder (Aux Encoder)                                     | 38 |
| Analog Encoder Phasing Reference Diagram                         | 65 |
| Analog Encoder Schematic (Aux Connector)                         | 66 |
| Analog Encoder Specifications (Feedback Connector)               | 38 |
| Analog I/O (AI/O) Connector [-EB1] Mating Connector Part Numbers | 67 |
| Analog I/O (AI/O) Connector Pinout [-EB1]                        | 67 |
| Analog Input [-EB1]  | 69 |
| Analog Input Pins (Analog I/O Connector [-EB1])                  | 69 |
| Analog Input Typical Connection [-EB1]                           | 69 |
| Analog Output Pins (Analog I/O Connector [-EB1])                 | 68 |
| Analog Output Specifications [-EB1]                              | 68 |
| Analog Output Typical Connection [-EB1]                          | 68 |
| Analog Outputs [-EB1]  | 68 |

|   |    |
|---|----|
| Aux Connector                               |    |
| Analog Encoder                              | 65 |
| Sine Wave Encoder                           | 65 |
| AUX Connector Mating Connector Part Numbers | 62 |
| AUX Connector Pinout                        | 62 |
| Aux Encoder Connector                       |    |
| Absolute Encoder                            | 64 |
| Analog Encoder                              | 38 |
| RS-422 Line Driver Encoder                  | 63 |
| Sine Wave Encoder                           | 38 |
| Square Wave Encoder                         | 63 |
| Auxiliary Encoder Connector Pinout          | 62 |
| Auxiliary Encoder Input [-EB1]              | 62 |

## B

|  |       |
|--|-------|
| BiSS absolute encoder  | 37,64 |
| Brake Connected to the Feedback Connector                    | 46    |
| Brake Control Relay Specifications                           | 46    |
| Brake Output Pins on the Feedback Connector                  | 46    |
| Brake Outputs (Feedback Connector)                           | 46    |
| Brushless Motor Configuration (Motor Power Output Connector) | 28    |
| Brushless Motor Connections (Motor Power Output Connector)   | 28    |
| Brushless Motor Phasing Goal                                 | 30    |
| Brushless Motor Phasing Oscilloscope Example                 | 30    |
| Brushless Motor Powered Motor Phasing                        | 29    |
| Brushless Motor Unpowered Motor and Feedback Phasing         | 30    |

## C

|   |    |
|---|----|
| Cable Wires   |    |
| Brushless Motors  | 28 |
| DC Brush Motors   | 31 |
| Stepper Motors  | 32 |
| Cables  |    |
| HyperWire   | 53 |
| Sync Port   | 54 |
| Cables and Accessories  | 75 |
| cables, examining   | 80 |
| Check for fluids or electrically conductive material exposure | 80 |
| Cleaning  | 80 |
| Commands  |    |
| Sync  | 54 |





|  |    |   |    |
|--|----|---|----|
| Thermistor Input   | 41 | TTL Outputs Schematic (PSO)                         | 61 |
| Travel Limit Input   | 43 | Typical STO Configuration                           | 48 |
| Feedback Monitoring  | 29 | fluids, dangerous                                   | 80 |
| Figure   |    | Functional Diagram                                  | 17 |
| -EB1 I/O Option Board Connectors                             | 59 | Fuse Specifications                                 | 81 |
| Absolute Encoder Schematic (Aux Encoder Connector)           | 64 | Control Supply at L                                 | 81 |
| Absolute Encoder Schematic (Feedback Connector)              | 37 | External Shunt (-SX1)                               | 81 |
| Analog Encoder Schematic (Aux Connector)                     | 66 | Motor Supply at AC1                                 | 81 |
| Analog Input Typical Connection [-EB1]                       | 69 |   |    |
| Analog Output Typical Connection [-EB1]                      | 68 | <b>H</b>  |    |
| Brake Connected to the Feedback Connector                    | 46 | Hall-Effect Feedback Pins on the Feedback Connector | 40 |
| Brushless Motor Configuration (Motor Power Output Connector) | 28 | Hall-Effect Inputs (Feedback Connector)             | 40 |
| Control Supply Connections                                   | 25 | Hall-Effect Inputs Schematic                        | 40 |
| DC Brush Motor Configuration (Motor Power Output Connector)  | 31 | Handling  | 13 |
| Digital Inputs Connected to a Current Sinking Device [-EB1]  | 74 | Handwheel Interconnection to the Aux Connector      | 78 |
| Digital Inputs Connected to a Current Sourcing Device [-EB1] | 74 | Handwheel Interface                                 | 78 |
| Digital Inputs Schematic [-EB1]                              | 73 | Home Limit Input (Feedback Connector)               | 43 |
| Digital Outputs Schematic [-EB1]                             | 71 | Home Limit Input Connections                        | 44 |
| Dimensions (without -EB1)                                    | 20 | Home Limit Input Diagnostic Display                 | 45 |
| Dimensions with -EB1   | 21 | Home Limit Input Pins on the Feedback Connector     | 43 |
| End of Travel Limit Input Connections                        | 44 | Humidity  | 22 |
| End of Travel Limit Input Diagnostic Display                 | 45 | HyperWire   | 53 |
| Hall-Effect Inputs Schematic                                 | 40 | Cable Part Numbers                                  | 53 |
| Home Limit Input Connections                                 | 44 | Card Part Number                                    | 53 |
| Home Limit Input Diagnostic Display                          | 45 | HyperWire-DIN                                       | 76 |
| Home Limit Input Pins on the Feedback Connector              | 43 |   |    |
| Humidity   | 22 | <b>I</b>  |    |
| HyperWire  | 53 | I/O Option Board [-EB1]                             | 59 |
| Cable Part Numbers   | 53 | Input Power Connections                             | 25 |
| Card Part Number   | 53 | inspecting cooling vents                            | 80 |
| HyperWire-DIN  | 76 | Inspection  | 80 |
|  |    | Installation and Configuration                      | 25 |
|  |    | Installation Overview                               | 14 |
|  |    | Introduction  | 15 |
|  |    | IP54 Compliant                                      | 19 |
|  |    | Isolated Output Current Sinks Schematic (PSO)       | 61 |
|  |    | Isolated Output Current Sources Schematic (PSO)     | 61 |
|  |    | <b>J</b>  |    |
|  |    | Joystick Interface                                  | 77 |
|  |    |   |    |
|  |    | <b>M</b>  |    |
|  |    | Maintenance   | 79 |



|  |       |  |    |
|--|-------|--|----|
| Safety Procedures and Warnings                           | 11    | Standards Data   | 49 |
| serial data stream                                       | 37,64 | Startup Validation Testing   | 51 |
| serial number  | 13    | Timing   | 52 |
| Sine Wave Encoder (Aux Connector)                        | 65    | Typical Configuration  | 48 |
| Sine Wave Encoder (Aux Encoder Connector)                | 38    | Storage  | 13 |
| Sine Wave Encoder Phasing Reference Diagram              | 65    | Sync-Related Commands  | 54 |
| Sine Wave Encoder Schematic (Aux Connector)              | 66    | Sync Port Cables   | 54 |
| Sine Wave Encoder Specifications (Feedback Connector)    | 38    | Sync Ports   | 54 |
| Specifications   |       | System part number   | 13 |
| Analog Encoder (Feedback Connector)                      | 38    |  |    |
| Analog Output [-EB1]                                     | 68    | <b>T</b>   |    |
| Brake Control Relay                                      | 46    | Table of Contents  | 3  |
| Control Board Fuses                                      | 81    | Thermistor Input (Feedback Connector)                                | 41 |
| Control Supply Connector Wiring                          | 25    | Thermistor Input Pin on the Feedback Connector                       | 41 |
| Differential Analog Input [-EB1]                         | 69    | Thermistor Input Schematic   | 41 |
| Digital Inputs [-EB1]                                    | 73    | Three Phase Stepper Motor Configuration                              | 33 |
| Digital Outputs [-EB1]                                   | 70    | Three Phase Stepper Motor Connections (Motor Power Output Connector) | 33 |
| Motor Supply Wiring                                      | 26    | Travel Limit Input (Feedback Connector)                              | 43 |
| PSO [-EB1]   | 60    | TTL Outputs Schematic (PSO)  | 61 |
| RS-422 Encoder (Feedback Connector)                      | 36,63 | Two Axis Joystick Interface  | 77 |
| Sine Wave Encoder (Feedback Connector)                   | 38    | Typical STO Configuration  | 48 |
| Square Wave Encoder (Feedback Connector)                 | 36,63 |  |    |
| STO Electrical Specifications                            | 48    | <b>U</b>   |    |
| Unit Weight  | 19    | Unit Weight  | 19 |
| Square Wave Encoder                                      | 36    | Use  | 22 |
| Square Wave Encoder (Aux Encoder)                        | 63    |  |    |
| Square Wave Encoder Schematic (Feedback Connector)       | 36    | <b>W</b>   |    |
| Square Wave Encoder Schematic [-EB1]                     | 63    | Warranty and Field Service   | 83 |
| Square Wave Encoder Specifications (Feedback Connector)  | 36,63 | Wire Colors for Aerotech-Supplied Brushless Motor Cables             | 28 |
| Standard Features  | 16    | Wire Colors for Aerotech-Supplied DC Brush Motor Cables              | 31 |
| Stepper Motor Configuration                              | 32    | Wire Colors for Aerotech-Supplied Stepper Motor Cables               | 32 |
| Stepper Motor Connections (Motor Power Output Connector) | 32    |  |    |
| Stepper Motor Phasing                                    | 32-33 |  |    |
| STO  | 47    |  |    |
| Connector Pinout   | 47    |  |    |
| Diagnostics  | 52    |  |    |
| Electrical Specifications                                | 48    |  |    |
| External Delay Timer                                     | 50    |  |    |
| Functional Description                                   | 50    |  |    |
| Mating Connector Part Numbers                            | 47    |  |    |
| Motor Function Relative to the STO Input State           | 51    |  |    |
| Signal Delay   | 51    |  |    |
| Standards  | 49    |  |    |

*This page intentionally left blank.*